



TABELLA PRESE DI FORZA

POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

Z.F.

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sens de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapter mntg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes /Notes
				VELsu	VELno		STD	SE/R				
4-90 3.79	POS	SX	2313 P 1 ^A	1669	1669	345	K245					
		SX	2 ^A	1669	1669	345						
	POS	SX	2314 P 1 ^A	1157	1157	420	K245					
		SX	2 ^A	1157	1157	420						
	POS	SX	2325 P	1669	1669	345	K245					
	POS	SX	2365 P	1157	1157	420	K245					
	POS	DX	81Z1 P	890	890	1000	K216					
	POS	SX	82Z1 P	1173	1173	300	K129	K712				
	POS	SX	83Z1 P 1 ^A	1173	1173	300	K129	K712				
		SX	2 ^A	1843	1843	200						
	POS	SX	86Z1 P	1602	1602	350	K783					
	POS	SX	86Z2 P	1404	1404	400	K783					
	POS	SX	86Z3 P	1186	1186	450	K783					
POS	SX	86Z4 P	821	821	500	K783						
4-90 4.17	POS	SX	2313 P 1 ^A	1519	1519	345	K245					
		SX	2 ^A	1519	1519	345						
	POS	SX	2314 P 1 ^A	1053	1053	420	K245					
		SX	2 ^A	1053	1053	420						
	POS	SX	2325 P	1519	1519	345	K245					
	POS	SX	2365 P	1053	1053	420	K245					
	POS	DX	81Z1 P	810	810	1000	K216					
	POS	SX	82Z1 P	1068	1068	300	K129	K712				
	POS	SX	83Z1 P 1 ^A	1068	1068	300	K129	K712				
		SX	2 ^A	1678	1678	200						
	POS	SX	86Z1 P	1458	1458	350	K783					
	POS	SX	86Z2 P	1278	1278	400	K783					
	POS	SX	86Z3 P	1080	1080	450	K783					
POS	SX	86Z4 P	748	748	500	K783						
4-120 GP 8.05	POS	SX	2300 P 1 ^A	1819	1819	345	K246		601K5440000			
		SX	2 ^A	1819	1819	345						
	POS	SX	2310 P 1 ^A	1261	1261	420	K246		601K5440000			
		SX	2 ^A	1261	1261	420						
	POS	SX	2325 P	1819	1819	345	K246		601K5440000			
	POS	SX	2365 P	1261	1261	420	K246		601K5440000			
	POS	DX	81Z1 P	970	970	1000	K219		601K5440000			
	POS	SX	82Z1 P	1278	1278	300	K131	K710	601K5440000			
	POS	SX	83Z1 P 1 ^A	1278	1278	300	K131	K710	601K5440000			
		SX	2 ^A	2009	2009	200						
	POS	SX	86Z1 P	1746	1746	350	K781		601K5440000			
	POS	SX	86Z2 P	1531	1531	400	K781		601K5440000			
	POS	SX	86Z3 P	1293	1293	450	K781		601K5440000			
POS	SX	86Z4 P	895	895	500	K781		601K5440000				
4-120 GP 9.16	POS	SX	2300 P 1 ^A	1599	1599	345	K246		601K5440000			
		SX	2 ^A	1599	1599	345						
	POS	SX	2310 P 1 ^A	1109	1109	420	K246		601K5440000			
		SX	2 ^A	1109	1109	420						
	POS	SX	2325 P	1599	1599	345	K246		601K5440000			
	POS	SX	2365 P	1109	1109	420	K246		601K5440000			
	POS	DX	81Z1 P	853	853	1000	K219		601K5440000			
POS	SX	82Z1 P	1124	1124	300	K131	K710	601K5440000				



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

Z.F.

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sens de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapter mntg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes
				VELsu	VELno		STD	SE/R				
	POS	SX	83Z1 P 1 ^A		1124	300	K131	K710	601K5440000			
		SX	2 ^A		1767	200						
	POS	SX	86Z1 P		1535	350	K781		601K5440000			
	POS	SX	86Z2 P		1346	400	K781		601K5440000			
	POS	SX	86Z3 P		1137	450	K781		601K5440000			
	POS	SX	86Z4 P		787	500	K781		601K5440000			
4-120 GP	10.91	POS	SX	2300 P 1 ^A	1500	345	K246		601K5440000			
		SX	2 ^A		1500	345						
		POS	SX	2310 P 1 ^A	1040	420	K246		601K5440000			
		SX	2 ^A		1040	420						
		POS	SX	2325 P	1500	345	K246		601K5440000			
		POS	SX	2365 P	1040	420	K246		601K5440000			
		POS	DX	81Z1 P	800	1000	K219		601K5440000			
		POS	SX	82Z1 P	1054	300	K131	K710	601K5440000			
		POS	SX	83Z1 P 1 ^A	1054	300	K131	K710	601K5440000			
		SX	2 ^A		1657	200						
		POS	SX	86Z1 P	1440	350	K781		601K5440000			
		POS	SX	86Z2 P	1262	400	K781		601K5440000			
		POS	SX	86Z3 P	1066	450	K781		601K5440000			
		POS	SX	86Z4 P	738	500	K781		601K5440000			
4-120 GP+Z90	9.16	POS	SX	2300 P 1 ^A	1599	345	K246		606X9100000			
		SX	2 ^A		1599	345						
		POS	SX	2310 P 1 ^A	1109	420	K246		606X9100000			
		SX	2 ^A		1109	420						
		POS	SX	2325 P	1599	345	K246		606X9100000			
		POS	SX	2365 P	1109	420	K246		606X9100000			
		POS	DX	81Z1 P	853	1000	K219		606X9100000			
		POS	SX	82Z1 P	1124	300	K131	K710	606X9100000			
		POS	SX	83Z1 P 1 ^A	1124	300	K131	K710	606X9100000			
		SX	2 ^A		1767	200						
		POS	SX	86Z1 P	1535	350	K781		606X9100000			
		POS	SX	86Z2 P	1346	400	K781		606X9100000			
		POS	SX	86Z3 P	1137	450	K781		606X9100000			
		POS	SX	86Z4 P	787	500	K781		606X9100000			
4-150 GP	9.09	POS	SX	2300 P 1 ^A	1556	345	K246		601K5500000			
		SX	2 ^A		1556	345						
		POS	SX	2310 P 1 ^A	1079	420	K246		601K5500000			
		SX	2 ^A		1079	420						
		POS	SX	2325 P	1556	345	K246		601K5500000			
		POS	SX	2365 P	1079	420	K246		601K5500000			
		POS	DX	81Z1 P	830	1000	K219		601K5500000			
		POS	SX	82Z1 P	1094	300	K131	K710	601K5500000			
		POS	SX	83Z1 P 1 ^A	1094	300	K131	K710	601K5500000			
		SX	2 ^A		1719	200						
		POS	SX	86Z1 P	1494	350	K781		601K5550000			
		POS	SX	86Z2 P	1310	400	K781		601K5550000			
		POS	SX	86Z3 P	1106	450	K781		601K5550000			
		POS	SX	86Z4 P	766	500	K781		601K5550000			
5-18/3	5.91	SX	DX	1038 M	325	140	K201					
5-18/3 INGR.SP.		SX	DX	1038 M	325	140	K236		602AD008000			



TABELLA PRESE DI FORZA
 POWER TAKE OFFS
 NEBENANTRIEBETABELLE
 TABLEAU PRISE DE FORCE

Z.F.

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sens de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapter mntg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes
				VELsu	VELno		STD	SE/R				
5-24 6.4	DX	DX	2076 P		978	200	K082					
5-24 6.34	DX	DX	2076 P		986	200	K082					
5-35 5.64	POS	SX	2311 P 1 ^A		1181	345	K244					
		SX	2 ^A		1181	345						
	POS	SX	2312 P 1 ^A		819	420	K244					
		SX	2 ^A		819	420						
	POS	SX	2345 P		1181	345	K244					
	POS	SX	2351 P		819	420	K244					
	POS	DX	8122 P		630	600	K216					
	POS	SX	8222 P		830	300	K128	K709				
	POS	SX	8223 P		830	300	K128	K709				43
	POS	SX	8322 P 1 ^A		830	300	K128	K709				
		SX	2 ^A		1305	200						
	POS	SX	8323 P 1 ^A		830	300	K128	K709				43
		SX	2 ^A		1305	200						
	POS	SX	86Z5 P		1134	350	K783					
POS	SX	86Z6 P		994	400	K783						
POS	SX	86Z7 P		840	450	K783						
POS	SX	86Z8 P		581	500	K783						
5-35 6.45	POS	SX	2311 P 1 ^A		1031	345	K244					
		SX	2 ^A		1031	345						
	POS	SX	2312 P 1 ^A		715	420	K244					
		SX	2 ^A		715	420						
	POS	SX	2345 P		1031	345	K244					
	POS	SX	2351 P		715	420	K244					
	POS	DX	8122 P		550	600	K216					
	POS	SX	8222 P		725	300	K128	K709				
	POS	SX	8223 P		725	300	K128	K709				43
	POS	SX	8322 P 1 ^A		725	300	K128	K709				
		SX	2 ^A		1139	200						
	POS	SX	8323 P 1 ^A		725	300	K128	K709				43
		SX	2 ^A		1139	200						
	POS	SX	86Z5 P		990	350	K783					
POS	SX	86Z6 P		868	400	K783						
POS	SX	86Z7 P		733	450	K783						
POS	SX	86Z8 P		508	500	K783						
5-35 6.75	POS	SX	2311 P 1 ^A		984	345	K244					
		SX	2 ^A		984	345						
	POS	SX	2312 P 1 ^A		682	420	K244					
		SX	2 ^A		682	420						
	POS	SX	2345 P		984	345	K244					
	POS	SX	2351 P		682	420	K244					
	POS	DX	8122 P		525	600	K216					
	POS	SX	8222 P		692	300	K128	K709				
	POS	SX	8223 P		692	300	K128	K709				43
	POS	SX	8322 P 1 ^A		692	300	K128	K709				
		SX	2 ^A		1087	200						
POS	SX	8323 P 1 ^A		692	300	K128	K709				43	
	SX	2 ^A		1087	200							
5-35 6.79	POS	SX	2311 P 1 ^A		1251	345	K244					

I dati riportati non sono vincolanti e possono subire variazioni senza preavviso - Technical specifications are not binding and can be changed without notice



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

Z.F.

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sense de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapter mntg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes /Notes
				VELsu	VELno		STD	SE/R				
							SX	2 ^A				
	POS	SX	2312 P 1 ^A		867	420	K244					
		SX	2 ^A		867	420						
	POS	SX	2345 P		1251	345	K244					
	POS	SX	2351 P		867	420	K244					
	POS	DX	81Z2 P		667	600	K216					
	POS	SX	82Z2 P		879	300	K128	K709				
	POS	SX	82Z3 P		879	300	K128	K709				43
	POS	SX	83Z2 P 1 ^A		879	300	K128	K709				
		SX	2 ^A		1381	200						
	POS	SX	83Z3 P 1 ^A		879	300	K128	K709				43
		SX	2 ^A		1381	200						
	POS	SX	86Z5 P		1201	350	K783					
	POS	SX	86Z6 P		1053	400	K783					
	POS	SX	86Z7 P		889	450	K783					
	POS	SX	86Z8 P		616	500	K783					
5-35	7.65	POS	SX	2311 P 1 ^A		868	345	K244				
			SX	2 ^A		868	345					
		POS	SX	2312 P 1 ^A		602	420	K244				
			SX	2 ^A		602	420					
		POS	SX	2345 P		868	345	K244				
		POS	SX	2351 P		602	420	K244				
		POS	DX	81Z2 P		463	600	K216				
		POS	SX	82Z2 P		610	300	K128	K709			
		POS	SX	82Z3 P		610	300	K128	K709			43
		POS	SX	83Z2 P 1 ^A		610	300	K128	K709			
			SX	2 ^A		959	200					
		POS	SX	83Z3 P 1 ^A		610	300	K128	K709			43
			SX	2 ^A		959	200					
		POS	SX	86Z5 P		833	350	K783				
		POS	SX	86Z6 P		731	400	K783				
		POS	SX	86Z7 P		617	450	K783				
		POS	SX	86Z8 P		427	500	K783				
5-35	8.02	POS	SX	2311 P 1 ^A		829	345	K244				
			SX	2 ^A		829	345					
		POS	SX	2312 P 1 ^A		575	420	K244				
			SX	2 ^A		575	420					
		POS	SX	2345 P		829	345	K244				
		POS	SX	2351 P		575	420	K244				
		POS	DX	81Z2 P		442	600	K216				
		POS	SX	82Z2 P		583	300	K128	K709			
		POS	SX	82Z3 P		583	300	K128	K709			43
		POS	SX	83Z2 P 1 ^A		583	300	K128	K709			
			SX	2 ^A		915	200					
		POS	SX	83Z3 P 1 ^A		583	300	K128	K709			43
			SX	2 ^A		915	200					
		POS	SX	86Z5 P		796	350	K783				
		POS	SX	86Z6 P		697	400	K783				
		POS	SX	86Z7 P		589	450	K783				
		POS	SX	86Z8 P		408	500	K783				



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

Z.F.

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sens de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapter mntg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes /Notas
				VELsu	VELno		STD	SE/R				
5-42 (EUROPA)	5.72	DX/SX	DX	2241 P		775	250	K491				
5-42 (U.S.A.)	5.72	DX/SX	DX	2241 P		766	250	K492		6036SP10000		
5-47 (U.S.A.)	5.72											
5-42	4.65	DX/SX	DX	2241 P		800	250	K006				
5-42	6.56	SX	DX	2206 P		980	250	K768		6036SP05000		
5-42	7.552	SX	DX	2205 P		950	250	K362		6036SP05000		
5-47 (U.S.A.)	5.08	A DX/SX	DX	2241 P		828	250	K493		6036SP07500		
5-50	5.3	POS	SX	2313 P 1^A		1224	345	K244				
6-65	6.37		SX	2^A		1224	345					
		POS	SX	2314 P 1^A		849	420	K244				
			SX	2^A		849	420					
		POS	SX	2325 P		1224	345	K244				
		POS	SX	2365 P		849	420	K244				
		POS	DX	81Z1 P		653	1000	K216				
		POS	SX	82Z1 P		861	300	K129	K712			
		POS	SX	83Z1 P 1^A		861	300	K129	K712			
			SX	2^A		1352	200					
		POS	SX	86Z1 P		1175	350	K783				
		POS	SX	86Z2 P		1030	400	K783				
		POS	SX	86Z3 P		870	450	K783				
		POS	SX	86Z4 P		603	500	K783				
5-50	5.5	POS	SX	2313 P 1^A		1153	345	K244				
			SX	2^A		1153	345					
		POS	SX	2314 P 1^A		800	420	K244				
			SX	2^A		800	420					
		POS	SX	2325 P		1153	345	K244				
		POS	SX	2365 P		800	420	K244				
		POS	DX	81Z1 P		615	1000	K216				
		POS	SX	82Z1 P		811	300	K129	K712			
		POS	SX	83Z1 P 1^A		811	300	K129	K712			
			SX	2^A		1274	200					
		POS	SX	86Z1 P		1107	350	K783				
		POS	SX	86Z2 P		970	400	K783				
		POS	SX	86Z3 P		820	450	K783				
		POS	SX	86Z4 P		568	500	K783				
5-50	6.2	POS	SX	2313 P 1^A		1022	345	K244				
			SX	2^A		1022	345					
		POS	SX	2314 P 1^A		708	420	K244				
			SX	2^A		708	420					
		POS	SX	2325 P		1022	345	K244				
		POS	SX	2365 P		708	420	K244				
		POS	DX	81Z1 P		545	1000	K216				
		POS	SX	82Z1 P		718	300	K129	K712			
		POS	SX	83Z1 P 1^A		718	300	K129	K712			
			SX	2^A		1129	200					
		POS	SX	86Z1 P		981	350	K783				
		POS	SX	86Z2 P		860	400	K783				
		POS	SX	86Z3 P		726	450	K783				
		POS	SX	86Z4 P		503	500	K783				
5-50	6.61	POS	SX	2313 P 1^A		958	345	K244				



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

Z.F.

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sens de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapter mtg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes
				VELsu	VELno		STD	SE/R				
							SX	2 ^A				
	POS	SX	2314 P 1 ^A		664	420	K244					
		SX	2 ^A		664	420						
	POS	SX	2325 P		958	345	K244					
	POS	SX	2365 P		664	420	K244					
	POS	DX	81Z1 P		511	1000	K216					
	POS	SX	82Z1 P		673	300	K129	K712				
	POS	SX	83Z1 P 1 ^A		673	300	K129	K712				
		SX	2 ^A		1058	200						
	POS	SX	86Z1 P		920	350	K783					
	POS	SX	86Z2 P		806	400	K783					
	POS	SX	86Z3 P		681	450	K783					
	POS	SX	86Z4 P		472	500	K783					
5-50	8.02	POS	SX 2313 P 1 ^A		791	345	K244					
			SX 2 ^A		791	345						
		POS	SX 2314 P 1 ^A		549	420	K244					
			SX 2 ^A		549	420						
		POS	SX 2325 P		791	345	K244					
		POS	SX 2365 P		549	420	K244					
		POS	DX 81Z1 P		422	1000	K216					
		POS	SX 82Z1 P		556	300	K129	K712				
		POS	SX 83Z1 P 1 ^A		556	300	K129	K712				
			SX 2 ^A		874	200						
		POS	SX 86Z1 P		760	350	K783					
		POS	SX 86Z2 P		666	400	K783					
		POS	SX 86Z3		563	450	K783					
		POS	SX 86Z4 P		390	500	K783					
5-50+GV80/5.3	6.61	POS	SX 2313 P 1 ^A	1194	958	345	K244					
			SX 2 ^A	1194	958	345						
		POS	SX 2314 P 1 ^A	828	664	420	K244					
			SX 2 ^A	828	664	420						
		POS	SX 2325 P	1194	958	345	K244					
		POS	SX 2365 P	828	664	420	K244					
		POS	DX 81Z1 P	637	511	1000	K216					
		POS	SX 82Z1 P	840	673	300	K129	K712				
		POS	SX 83Z1 P 1 ^A	840	673	300	K129	K712				
			SX 2 ^A	1319	1058	200						
		POS	SX 86Z1 P	1147	920	350	K783					
		POS	SX 86Z2 P	1005	806	400	K783					
		POS	SX 86Z3 P	849	681	450	K783					
		POS	SX 86Z4 P	588	472	500	K783					
5-50+GV80/6.20	8.02	POS	SX 2313 P 1 ^A	1024	791	345	K244					
			SX 2 ^A	1024	791	345						
		POS	SX 2314 P 1 ^A	710	549	420	K244					
			SX 2 ^A	710	549	420						
		POS	SX 2325 P	1024	791	345	K244					
		POS	SX 2365 P	710	549	420	K244					
		POS	DX 81Z1 P	546	422	1000	K216					
		POS	SX 82Z1 P	720	556	300	K129	K712				
		POS	SX 83Z1 P 1 ^A	720	556	300	K129	K712				



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

Z.F.

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sens de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapter mntg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes /Notes
				VELsu	VELno		STD	SE/R				
		SX	2 ^A	1131	874	200						
	POS	SX	86Z1 P	983	760	350	K783					
	POS	SX	86Z2 P	862	666	400	K783					
	POS	SX	86Z3 P	728	563	450	K783					
	POS	SX	86Z4 P	504	390	500	K783					
5-90 GP	13.01	POS	SX	2300 P 1 ^A	1669	345	K246		601K5440000			
5-90 GPA			SX	2 ^A	1669	345						
5-92 GP	13.01	POS	SX	2310 P 1 ^A	1157	420	K246		601K5440000			
5K91 GP	13.01		SX	2 ^A	1157	420						
		POS	SX	2325 P	1669	345	K246		601K5440000			
		POS	SX	2365 P	1157	420	K246		601K5440000			
		POS	DX	81Z1 P	890	1000	K219		601K5440000			
		POS	SX	82Z1 P	1173	300	K131	K710	601K5440000			
		POS	SX	83Z1 P 1 ^A	1173	300	K131	K710	601K5440000			
			SX	2 ^A	1843	200						
		POS	SX	86Z1 P	1602	350	K781		601K5440000			
		POS	SX	86Z2 P	1404	400	K781		601K5440000			
		POS	SX	86Z3 P	1186	450	K781		601K5440000			
		POS	SX	86Z4 P	821	500	K781		601K5440000			
5-110 GP	8.26	POS	SX	2300 P 1 ^A	1828	345	K244		601K5500000			
			SX	2 ^A	1828	345						
		POS	SX	2310 P 1 ^A	1268	420	K244		601K5500000			
			SX	2 ^A	1268	420						
		POS	SX	2325 P	1828	345	K244		601K5500000			
		POS	SX	2365 P	1268	420	K244		601K5500000			
		POS	DX	81Z1 P	975	1000	K216		601K5500000			
		POS	SX	82Z1 P	1285	300	K129	K712	601K5500000			
		POS	SX	83Z1 P 1 ^A	1285	300	K129	K712	601K5500000			
			SX	2 ^A	2019	200						
		POS	SX	86Z1 P	1755	350	K783		601K5500000			
		POS	SX	86Z2 P	1539	400	K783		601K5500000			
		POS	SX	86Z3 P	1300	450	K783		601K5500000			
		POS	SX	86Z4 P	900	500	K783		601K5500000			
5-110 GP	9.72	POS	SX	2300 P 1 ^A	1556	345	K244		601K5500000			
5-110 GP	13.1		SX	2 ^A	1556	345						
5-110 GPU	13.4	POS	SX	2310 P 1 ^A	1079	420	K244		601K5500000			
5-111 GP	13.04		SX	2 ^A	1079	420						
		POS	SX	2325 P	1556	345	K244		601K5500000			
		POS	SX	2365 P	1079	420	K244		601K5500000			
		POS	DX	81Z1 P	830	1000	K216		601K5500000			
		POS	SX	82Z1 P	1094	300	K129	K712	601K5500000			
		POS	SX	83Z1 P 1 ^A	1094	300	K129	K712	601K5500000			
			SX	2 ^A	1719	200						
		POS	SX	86Z1 P	1494	350	K783		601K5500000			
		POS	SX	86Z2 P	1310	400	K783		601K5500000			
		POS	SX	86Z3 P	1106	450	K783		601K5500000			
		POS	SX	86Z4 P	766	500	K783		601K5500000			
5-110 GP	11.2	POS	SX	2310 P 1 ^A	1268	420	K244		601K5500000			
			SX	2 ^A	1268	420						
		POS	SX	2325 P	1828	345	K244		601K5500000			



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

Z.F.

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sens de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapt. mtg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes /Notes
				VELsu	VELno		STD	SE/R				
	POS	SX	2365 P		1268	420	K244		601K5500000			
	POS	DX	81Z1 P		975	1000	K216		601K5500000			
	POS	SX	82Z1 P		1285	300	K129	K712	601K5500000			
	POS	SX	83Z1 P 1 ^A		1285	300	K129	K712	601K5500000			
		SX	2 ^A		2019	200						
	POS	SX	86Z1 P		1755	350	K783		601K5500000			
	POS	SX	86Z2 P		1539	400	K783		601K5500000			
	POS	SX	86Z3 P		1300	450	K783		601K5500000			
	POS	SX	86Z4 P		900	500	K783		601K5500000			
5-110 GP+GV91	13.1	POS	SX	2300 P 1 ^A	1836	1556	345	K244		601K5500000		
			SX	2 ^A	1836	1556	345					
		POS	SX	2310 P 1 ^A	1273	1079	420	K244		601K5500000		
			SX	2 ^A	1273	1079	420					
		POS	SX	2325 P	1836	1556	345	K244		601K5500000		
		POS	SX	2365 P	1273	1079	420	K244		601K5500000		
		POS	DX	81Z1 P	979	830	1000	K216		601K5500000		
		POS	SX	82Z1 P	1290	1094	300	K129	K712	601K5500000		
		POS	SX	83Z1 P 1 ^A	1290	1094	300	K129	K712	601K5500000		
			SX	2 ^A	2028	1719	200					
		POS	SX	86Z1 P	1762	1494	350	K783		601K5500000		
		POS	SX	86Z2 P	1545	1310	400	K783		601K5500000		
		POS	SX	86Z3 P	1305	1106	450	K783		601K5500000		
		POS	SX	86Z4 P	904	766	500	K783		601K5500000		
5-111 GP+GV 91	13.04	POS	SX	2310 P 1 ^A	1273	1079	420	K244		601K5500000		
			SX	2 ^A	1273	1079	420					
		POS	SX	2325 P	1836	1556	345	K244		601K5500000		
		POS	SX	2365 P	1273	1079	420	K244		601K5500000		
		POS	DX	81Z1 P	979	830	1000	K216		601K5500000		
		POS	SX	82Z1 P	1290	1094	300	K129	K712	601K5500000		
		POS	SX	83Z1 P 1 ^A	1290	1094	300	K129	K712	601K5500000		
			SX	2 ^A	2028	1719	200					
		POS	SX	86Z1 P	1762	1494	350	K783		601K5500000		
		POS	SX	86Z2 P	1545	1310	400	K783		601K5500000		
		POS	SX	86Z3 P	1305	1106	450	K783		601K5500000		
		POS	SX	86Z4 P	904	766	500	K783		601K5500000		
5-150	4.2	POS	SX	2313 P 1 ^A		1444	345	K245				
			SX	2 ^A		1444	345					
		POS	SX	2314 P 1 ^A		1001	420	K245				
			SX	2 ^A		1001	420					
		POS	SX	2325 P		1444	345	K245				
		POS	SX	2365 P		1001	420	K245				
		POS	DX	81Z1 P		770	1000	K216				
		POS	SX	82Z1 P		1015	300	K129	K712			
		POS	SX	83Z1 P 1 ^A		1015	300	K129	K712			
			SX	2 ^A		1595	200					
		POS	SX	86Z1 P		1386	350	K783				
		POS	SX	86Z2 P		1215	400	K783				
		POS	SX	86Z3 P		1026	450	K783				
		POS	SX	86Z4 P		711	500	K783				
5-150	5.03	POS	SX	2313 P 1 ^A		1200	345	K245				



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

Z.F.

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sens de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapter mtg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes
				VELsu	VELno		STD	SE/R				
							SX	2 ^A				
	POS	SX	2314 P 1 ^A		832	420	K245					
		SX	2 ^A		832	420						
	POS	SX	2325 P		1200	345	K245					
	POS	SX	2365 P		832	420	K245					
	POS	DX	81Z1 P		640	1000	K216					
	POS	SX	82Z1 P		844	300	K129	K712				
	POS	SX	83Z1 P 1 ^A		844	300	K129	K712				
		SX	2 ^A		1325	200						
	POS	SX	86Z1 P		1152	350	K783					
	POS	SX	86Z2 P		1010	400	K783					
	POS	SX	86Z3 P		853	450	K783					
	POS	SX	86Z4 P		591	500	K783					
5-680	7.43	POS	SX	2345 P		806	345	K246				
		POS	DX	81Z2 P		430	600	K216				
		POS	SX	82Z2 P		567	300	K128	K709			
		POS	SX	82Z3 P		567	300	K128	K709			43
		POS	SX	83Z2 P 1 ^A		567	300	K128	K709			
			SX	2 ^A		891	200					
		POS	SX	83Z3 P 1 ^A		567	300	K128	K709			43
			SX	2 ^A		891	200					
		POS	SX	86Z5 P		774	350	K783				
		POS	SX	86Z6 P		679	400	K783				
		POS	SX	86Z7 P		573	450	K783				
		POS	SX	86Z8 P		397	500	K783				
6 S 850 DT 1.00	8.51	POS	SX	2311 P 1 ^A		788	345	K246				
			SX	2 ^A		788	345					
		POS	SX	2312 P 1 ^A		546	420	K246				
			SX	2 ^A		546	420					
		POS	SX	2345 P		788	345	K246				
		POS	SX	2351 P		546	420	K246				
		POS	DX	81Z2 P		420	600	K219				
		POS	SX	82Z2 P		554	300	K719	K720			
		POS	SX	82Z3 P		554	300	K719	K720			43
		POS	SX	83Z2 P 1 ^A		554	300	K719	K720			
			SX	2 ^A		870	200					
		POS	SX	83Z3 P 1 ^A		554	300	K131	K710			43
			SX	2 ^A		870	200					
		POS	SX	86Z5 P		756	350	K781				
		POS	SX	86Z6 P		663	400	K781				
		POS	SX	86Z7 P		560	450	K781				
		POS	SX	86Z8 P		388	500	K781				
6 S 850 OD 0.79	6.72	POS	SX	2311 P 1 ^A		999	345	K246				
			SX	2 ^A		999	345					
		POS	SX	2312 P 1 ^A		693	420	K246				
			SX	2 ^A		693	420					
		POS	SX	2345 P		999	345	K246				
		POS	SX	2351 P		693	420	K246				
		POS	DX	81Z2 P		533	600	K219				
		POS	SX	82Z2 P		702	300	K719	K720			



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

Z.F.

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sens de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapter mntg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes /Notes
				VELsu	VELno		STD	SE/R				
					POS		SX	82Z3 P				
	POS	SX	83Z2 P 1 ^A		702	300	K719	K720				
		SX	2 ^A		1104	200						
	POS	SX	83Z3 P 1 ^A		702	300	K131	K710				43
		SX	2 ^A		1104	200						
	POS	SX	86Z5 P		959	350	K781					
	POS	SX	86Z6 P		841	400	K781					
	POS	SX	86Z7 P		710	450	K781					
	POS	SX	86Z8 P		492	500	K781					
6-36	6.06	POS	SX	2311 P 1 ^A		1095	345	K246				
			SX	2 ^A		1095	345					
		POS	SX	2312 P 1 ^A		759	420	K246				
			SX	2 ^A		759	420					
		POS	SX	2345 P		1095	345	K246				
		POS	SX	2351 P		759	420	K246				
		POS	DX	81Z2 P		584	600	K219				
		POS	SX	82Z2 P		770	300	K719	K720			
		POS	SX	82Z3 P		770	300	K719	K720			43
		POS	SX	83Z2 P 1 ^A		770	300	K719	K720			
			SX	2 ^A		1209	200					
		POS	SX	83Z3 P 1 ^A		770	300	K131	K710			43
			SX	2 ^A		1209	200					
		POS	SX	86Z5 P		1051	350	K781				
		POS	SX	86Z6 P		922	400	K781				
		POS	SX	86Z7 P		778	450	K781				
		POS	SX	86Z8 P		539	500	K781				
6-36	7.43	POS	SX	2311 P 1 ^A		900	345	K246				
			SX	2 ^A		900	345					
		POS	SX	2312 P 1 ^A		624	420	K246				
			SX	2 ^A		624	420					
		POS	SX	2345 P		900	345	K246				
		POS	SX	2351 P		624	420	K246				
		POS	DX	81Z2 P		480	600	K219				
		POS	SX	82Z2 P		633	300	K719	K720			
		POS	SX	82Z3 P		633	300	K719	K720			43
		POS	SX	83Z2 P 1 ^A		633	300	K719	K720			
			SX	2 ^A		994	200					
		POS	SX	83Z3 P 1 ^A		633	300	K131	K710			43
			SX	2 ^A		994	200					
		POS	SX	86Z5 P		864	350	K781				
		POS	SX	86Z6 P		757	400	K781				
		POS	SX	86Z7 P		640	450	K781				
		POS	SX	86Z8 P		443	500	K781				
6-36	8.97	DX	DX	2174 P		966	250	K769		6036SP07500		
		POS	SX	2311 P 1 ^A		750	345	K246				
			SX	2 ^A		750	345					
		POS	SX	2312 P 1 ^A		520	420	K246				
			SX	2 ^A		520	420					
		POS	SX	2345 P		750	345	K246				
		POS	SX	2351 P		520	420	K246				



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

Z.F.

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sens de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapt. mntg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes
				VELsu	VELno		STD	SE/R				
	POS	DX	81Z2 P		400	600	K219					
	POS	SX	82Z2 P		527	300	K719	K720				
	POS	SX	82Z3 P		527	300	K719	K720				43
	POS	SX	83Z2 P 1 ^A		527	300	K719	K720				
		SX	2 ^A		828	200						
	POS	SX	83Z3 P 1 ^A		527	300	K131	K710				43
		SX	2 ^A		828	200						
	POS	SX	86Z5 P		720	350	K781					
	POS	SX	86Z6 P		631	400	K781					
	POS	SX	86Z7 P		533	450	K781					
	POS	SX	86Z8 P		369	500	K781					
6-36+GV36/6.32	7.43	POS	SX	2311 P 1 ^A	1050	900	345	K246				
			SX	2 ^A	1050	900	345					
		POS	SX	2312 P 1 ^A	728	624	420	K246				
			SX	2 ^A	728	624	420					
		POS	SX	2345 P	1050	900	345	K246				
		POS	SX	2351 P	728	624	420	K246				
		POS	DX	81Z2 P	560	480	600	K219				
		POS	SX	82Z2 P	738	633	300	K719	K720			
		POS	SX	82Z3 P	738	633	300	K719	K720			43
		POS	SX	83Z2 P 1 ^A	738	633	300	K719	K720			
			SX	2 ^A	1160	994	200					
		POS	SX	83Z3 P 1 ^A	738	633	300	K131	K710			43
			SX	2 ^A	1160	994	200					
		POS	SX	86Z5 P	1008	864	350	K781				
		POS	SX	86Z6 P	884	757	400	K781				
		POS	SX	86Z7 P	746	640	450	K781				
		POS	SX	86Z8 P	517	443	500	K781				
6-36+GV36/7.43	8.97	DX	DX	2174 P	1166	966	250	K769		6036SP07500		
		POS	SX	2311 P 1 ^A	906	750	345	K246				
			SX	2 ^A	906	750	345					
		POS	SX	2312 P 1 ^A	628	520	420	K246				
			SX	2 ^A	628	520	420					
		POS	SX	2345 P	906	750	345	K246				
		POS	SX	2351 P	628	520	420	K246				
		POS	DX	81Z2 P	483	400	600	K219				
		POS	SX	82Z2 P	637	527	300	K719	K720			
		POS	SX	82Z3 P	637	527	300	K719	K720			43
		POS	SX	83Z2 P 1 ^A	637	527	300	K719	K720			
			SX	2 ^A	1000	828	200					
		POS	SX	83Z3 P 1 ^A	637	527	300	K131	K710			43
			SX	2 ^A	1000	828	200					
		POS	SX	86Z5 P	869	720	350	K781				
		POS	SX	86Z6 P	762	631	400	K781				
		POS	SX	86Z7 P	644	533	450	K781				
		POS	SX	86Z8 P	446	369	500	K781				
6-65	6.7	POS	SX	2313 P 1 ^A		1166	345	K244				
			SX	2 ^A		1166	345					
		POS	SX	2314 P 1 ^A		809	420	K244				
			SX	2 ^A		809	420					



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

Z.F.

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sens de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapter mtg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes /Notes
				VELsu	VELno		STD	SE/R				
					POS		SX	2325 P				
	POS	SX	2365 P		809	420	K244					
	POS	DX	81Z1 P		622	1000	K216					
	POS	SX	82Z1 P		820	300	K129	K712				
	POS	SX	83Z1 P 1 ^A		820	300	K129	K712				
		SX	2 ^A		1288	200						
	POS	SX	86Z1 P		1120	350	K783					
	POS	SX	86Z2 P		982	400	K783					
	POS	SX	86Z3 P		829	450	K783					
	POS	SX	86Z4 P		574	500	K783					
6-65	7.4	POS	SX	2313 P 1 ^A		1054	345	K244				
			SX	2 ^A		1054	345					
		POS	SX	2314 P 1 ^A		731	420	K244				
			SX	2 ^A		731	420					
		POS	SX	2325 P		1054	345	K244				
		POS	SX	2365 P		731	420	K244				
		POS	DX	81Z1 P		562	1000	K216				
		POS	SX	82Z1 P		741	300	K129	K712			
		POS	SX	83Z1 P 1 ^A		741	300	K129	K712			
			SX	2 ^A		1164	200					
		POS	SX	86Z1 P		1012	350	K783				
		POS	SX	86Z2 P		887	400	K783				
		POS	SX	86Z3 P		749	450	K783				
		POS	SX	86Z4 P		519	500	K783				
6-65	7.52	POS	SX	2313 P 1 ^A		1041	345	K244				
6-80	7.53		SX	2 ^A		1041	345					
		POS	SX	2314 P 1 ^A		722	420	K244				
			SX	2 ^A		722	420					
		POS	SX	2325 P		1041	345	K244				
		POS	SX	2365 P		722	420	K244				
		POS	DX	81Z1 P		555	1000	K216				
		POS	SX	82Z1 P		731	300	K129	K712			
		POS	SX	83Z1 P 1 ^A		731	300	K129	K712			
			SX	2 ^A		1149	200					
		POS	SX	86Z1 P		999	350	K783				
		POS	SX	86Z2 P		876	400	K783				
		POS	SX	86Z3 P		740	450	K783				
		POS	SX	86Z4 P		512	500	K783				
6-65	9	POS	SX	2313 P 1 ^A		868	345	K244				
			SX	2 ^A		868	345					
		POS	SX	2314 P 1 ^A		602	420	K244				
			SX	2 ^A		602	420					
		POS	SX	2325 P		868	345	K244				
		POS	SX	2365 P		602	420	K244				
		POS	DX	81Z1 P		463	1000	K216				
		POS	SX	82Z1 P		610	300	K129	K712			
		POS	SX	83Z1 P 1 ^A		610	300	K129	K712			
			SX	2 ^A		959	200					
		POS	SX	86Z1 P		833	350	K783				
		POS	SX	86Z2 P		731	400	K783				



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

Z.F.

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sens de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapt. mtg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes /Notes
				VELsu	VELno		STD	SE/R				
	POS	SX	86Z3 P		617	450	K783					
	POS	SX	86Z4 P		427	500	K783					
6-65+GV70/7.67	POS	SX	2313 P 1^	857	684	345	K244					
		SX	2^	857	684	345						
	POS	SX	2314 P 1^	594	474	420	K244					
		SX	2^	594	474	420						
	POS	SX	2325 P	857	684	345	K244					
	POS	SX	2365 P	594	474	420	K244					
	POS	DX	81Z1 P	457	365	1000	K216					
	POS	SX	82Z1 P	602	481	300	K129	K712				
	POS	SX	83Z1 P 1^	602	481	300	K129	K712				
		SX	2^	946	756	200						
	POS	SX	86Z1 P	823	657	350	K783					
	POS	SX	86Z2 P	721	576	400	K783					
	POS	SX	86Z3 P	609	487	450	K783					
	POS	SX	86Z4 P	422	337	500	K783					
6-65+GV80/6.7 7.97	POS	SX	2313 P 1^	1166	986	345	K244					
		SX	2^	1166	986	345						
	POS	SX	2314 P 1^	809	684	420	K244					
		SX	2^	809	684	420						
	POS	SX	2325 P	1166	986	345	K244					
	POS	SX	2365 P	809	684	420	K244					
	POS	DX	81Z1 P	622	526	1000	K216					
	POS	SX	82Z1 P	820	693	300	K129	K712				
	POS	SX	83Z1 P 1^	820	693	300	K129	K712				
		SX	2^	1288	1089	200						
	POS	SX	86Z1 P	1120	947	350	K783					
	POS	SX	86Z2 P	982	830	400	K783					
	POS	SX	86Z3 P	829	701	450	K783					
	POS	SX	86Z4 P	574	485	500	K783					
6-65+GV80/6.7 9	POS	SX	2313 P 1^	1166	868	345	K244					
		SX	2^	1166	868	345						
	POS	SX	2314 P 1^	809	602	420	K244					
		SX	2^	809	602	420						
	POS	SX	2325 P	1166	868	345	K244					
	POS	SX	2365 P	809	602	420	K244					
	POS	DX	81Z1 P	622	463	1000	K216					
	POS	SX	82Z1 P	820	610	300	K129	K712				
	POS	SX	83Z1 P 1^	820	610	300	K129	K712				
		SX	2^	1288	959	200						
	POS	SX	86Z1 P	1120	833	350	K783					
	POS	SX	86Z2 P	982	731	400	K783					
	POS	SX	86Z3 P	829	617	450	K783					
	POS	SX	86Z4 P	574	427	500	K783					
6-65+GV80/7.52 9	POS	SX	2313 P 1^	1042	868	345	K244					
		SX	2^	1042	868	345						
	POS	SX	2314 P 1^	723	602	420	K244					
		SX	2^	723	602	420						
	POS	SX	2325 P	1042	868	345	K244					
	POS	SX	2365 P	723	602	420	K244					



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

Z.F.

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sens de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapter mntg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes /Notes
				VELsu	VELno		STD	SE/R				
					POS		DX	81Z1 P				
	POS	SX	82Z1 P	733	610	300	K129	K712				
	POS	SX	83Z1 P 1 ^A	733	610	300	K129	K712				
		SX	2 ^A	1151	959	200						
	POS	SX	86Z1 P	1001	833	350	K783					
	POS	SX	86Z2 P	877	731	400	K783					
	POS	SX	86Z3 P	741	617	450	K783					
	POS	SX	86Z4 P	513	427	500	K783					
6-66	6.78	POS	SX	2313 P 1 ^A	1050	345	K246				53	
			SX	2 ^A	1050	345						
		POS	SX	2314 P 1 ^A	728	420	K246				53	
			SX	2 ^A	728	420						
		POS	SX	2325 P	1050	345	K246				53	
		POS	SX	2365 P	728	420	K246				53	
		POS	DX	81Z1 P	560	1000	K219					
		POS	SX	82Z1 P	738	300	K131	K710				
		POS	SX	83Z1 P 1 ^A	738	300	K131	K710				
			SX	2 ^A	1160	200						
		POS	SX	86Z1 P	1008	350	K781					
		POS	SX	86Z2 P	884	400	K781					
		POS	SX	86Z3 P	746	450	K781					
		POS	SX	86Z4 P	517	500	K781					
6-66	7.36	POS	SX	2313 P 1 ^A	975	345	K246				53	
			SX	2 ^A	975	345						
		POS	SX	2314 P 1 ^A	676	420	K246				53	
			SX	2 ^A	676	420						
		POS	SX	2325 P	975	345	K246				53	
		POS	SX	2365 P	676	420	K246				53	
		POS	DX	81Z1 P	520	1000	K219					
		POS	SX	82Z1 P	685	300	K131	K710				
		POS	SX	83Z1 P 1 ^A	685	300	K131	K710				
			SX	2 ^A	1077	200						
		POS	SX	86Z1 P	936	350	K781					
		POS	SX	86Z2 P	821	400	K781					
		POS	SX	86Z3 P	693	450	K781					
		POS	SX	86Z4 P	480	500	K781					
6-66	9.06	POS	SX	2313 P 1 ^A	788	345	K246				53	
			SX	2 ^A	788	345						
		POS	SX	2314 P 1 ^A	546	420	K246				53	
			SX	2 ^A	546	420						
		POS	SX	2325 P	788	345	K246				53	
		POS	SX	2365 P	546	420	K246				53	
		POS	DX	81Z1 P	420	1000	K219					
		POS	SX	82Z1 P	554	300	K131	K710				
		POS	SX	83Z1 P 1 ^A	554	300	K131	K710				
			SX	2 ^A	870	200						
		POS	SX	86Z1 P	756	350	K781					
		POS	SX	86Z2 P	663	400	K781					
		POS	SX	86Z3 P	560	450	K781					
		POS	SX	86Z4 P	388	500	K781					



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

Z.F.

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sense de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapter mntg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes
				VELsu	VELno		STD	SE/R				
				6-66+GV66/6.37 9.06	POS		SX	2313 P 1 [^]				
6-66+GV66/7.51 9.06		SX	2 [^]	956	788	345						
	POS	SX	2314 P 1 [^]	663	546	420	K246					53
		SX	2 [^]	663	546	420						
	POS	SX	2325 P	956	788	345	K246					53
	POS	SX	2365 P	663	546	420	K246					53
	POS	DX	81Z1 P	510	420	1000	K219					
	POS	SX	82Z1 P	672	554	300	K131	K710				
	POS	SX	83Z1 P 1 [^]	672	554	300	K131	K710				
		SX	2 [^]	1056	870	200						
	POS	SX	86Z1 P	918	756	350	K781					
	POS	SX	86Z2 P	805	663	400	K781					
	POS	SX	86Z3 P	680	560	450	K781					
	POS	SX	86Z4 P	471	388	500	K781					
6-70 6.8	POS	SX	2313 P 1 [^]		956	345	K244					
		SX	2 [^]		956	345						
	POS	SX	2314 P 1 [^]		663	420	K244					
		SX	2 [^]		663	420						
	POS	SX	2325 P		956	345	K244					
	POS	SX	2365 P		663	420	K244					
	POS	DX	81Z1 P		510	1000	K216					
	POS	SX	82Z1 P		672	300	K129	K712				
	POS	SX	83Z1 P 1 [^]		672	300	K129	K712				
		SX	2 [^]		1056	200						
	POS	SX	86Z1 P		918	350	K783					
	POS	SX	86Z2 P		805	400	K783					
	POS	SX	86Z3 P		680	450	K783					
	POS	SX	86Z4 P		471	500	K783					
6-70 7.36	POS	SX	2313 P 1 [^]		896	345	K244					
		SX	2 [^]		896	345						
	POS	SX	2314 P 1 [^]		621	420	K244					
		SX	2 [^]		621	420						
	POS	SX	2325 P		896	345	K244					
	POS	SX	2365 P		621	420	K244					
	POS	DX	81Z1 P		478	1000	K216					
	POS	SX	82Z1 P		630	300	K129	K712				
	POS	SX	83Z1 P 1 [^]		630	300	K129	K712				
		SX	2 [^]		990	200						
	POS	SX	86Z1 P		860	350	K783					
	POS	SX	86Z2 P		754	400	K783					
	POS	SX	86Z3 P		637	450	K783					
	POS	SX	86Z4 P		441	500	K783					
6-70 7.92	POS	SX	2313 P 1 [^]		825	345	K244					
		SX	2 [^]		825	345						
	POS	SX	2314 P 1 [^]		572	420	K244					
		SX	2 [^]		572	420						
	POS	SX	2325 P		825	345	K244					
	POS	SX	2365 P		572	420	K244					
	POS	DX	81Z1 P		440	1000	K216					
	POS	SX	82Z1 P		580	300	K129	K712				



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

Z.F.

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sense de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapt. mntg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes
				VELsu	VELno		STD	SE/R				
	POS	SX	83Z1 P 1 ^A		580	300	K129	K712				
		SX	2 ^A		911	200						
6-70	9.03	POS	2313 P 1 ^A		728	345	K244					
		SX	2 ^A		728	345						
		POS	2314 P 1 ^A		504	420	K244					
		SX	2 ^A		504	420						
		POS	2325 P		728	345	K244					
		POS	2365 P		504	420	K244					
		POS	81Z1 P		388	1000	K216					
		POS	82Z1 P		511	300	K129	K712				
		POS	83Z1 P 1 ^A		511	300	K129	K712				
		SX	2 ^A		804	200						
		POS	86Z1 P		698	350	K783					
		POS	86Z2 P		612	400	K783					
		POS	86Z3 P		517	450	K783					
		POS	86Z4 P		358	500	K783					
6-70	9.59	POS	2313 P 1 ^A		686	345	K244					
		SX	2 ^A		686	345						
		POS	2314 P 1 ^A		476	420	K244					
		SX	2 ^A		476	420						
		POS	2325 P		686	345	K244					
		POS	2365 P		476	420	K244					
		POS	81Z1 P		366	1000	K216					
		POS	82Z1 P		482	300	K129	K712				
		POS	83Z1 P 1 ^A		482	300	K129	K712				
		SX	2 ^A		758	200						
		POS	86Z1 P		659	350	K783					
		POS	86Z2 P		578	400	K783					
		POS	86Z3 P		488	450	K783					
		POS	86Z4 P		338	500	K783					
6-70+GV70/5.71	6.8	POS	2313 P 1 ^A	1149	956	345	K244					
		SX	2 ^A	1149	956	345						
		POS	2314 P 1 ^A	797	663	420	K244					
		SX	2 ^A	797	663	420						
		POS	2325 P	1149	956	345	K244					
		POS	2365 P	797	663	420	K244					
		POS	81Z1 P	613	510	1000	K216					
		POS	82Z1 P	808	672	300	K129	K712				
		POS	83Z1 P 1 ^A	808	672	300	K129	K712				
		SX	2 ^A	1270	1056	200						
		POS	86Z1 P	1103	918	350	K783					
		POS	86Z2 P	967	805	400	K783					
		POS	86Z3 P	817	680	450	K783					
		POS	86Z4 P	566	471	500	K783					
6-75+GV80/7.52	6.7	POS	2313 P 1 ^A	1166	1042	345	K244					
		SX	2 ^A	1166	1042	345						
		POS	2314 P 1 ^A	809	723	420	K244					
		SX	2 ^A	809	723	420						
		POS	2325 P	1166	1042	345	K244					
		POS	2365 P	809	723	420	K244					



TABELLA PRESE DI FORZA

POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

Z.F.

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sens de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapter mntg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes
				VELsu	VELno		STD	SE/R				
					POS		DX	81Z1 P				
	POS	SX	82Z1 P	820	733	300	K129	K712				
	POS	SX	83Z1 P 1 ^A	820	733	300	K129	K712				
		SX	2 ^A	1288	1151	200						
	POS	SX	86Z1 P	1120	1001	350	K783					
	POS	SX	86Z2 P	982	877	400	K783					
	POS	SX	86Z3 P	829	741	450	K783					
	POS	SX	86Z4 P	574	513	500	K783					
6-80	5.03	POS	SX	2313 P 1 ^A		1462	345	K244				
			SX	2 ^A		1462	345					
		POS	SX	2314 P 1 ^A		1014	420	K244				
			SX	2 ^A		1014	420					
		POS	SX	2325 P		1462	345	K244				
		POS	SX	2365 P		1014	420	K244				
		POS	DX	81Z1 P		780	1000	K216				
		POS	SX	82Z1 P		1028	300	K129	K712			
		POS	SX	83Z1 P 1 ^A		1028	300	K129	K712			
			SX	2 ^A		1615	200					
		POS	SX	86Z1 P		1404	350	K783				
		POS	SX	86Z2 P		1231	400	K783				
		POS	SX	86Z3 P		1040	450	K783				
		POS	SX	86Z4 P		720	500	K783				
6-80	5.66	POS	SX	2313 P 1 ^A		1384	345	K244				
			SX	2 ^A		1384	345					
		POS	SX	2314 P 1 ^A		959	420	K244				
			SX	2 ^A		959	420					
		POS	SX	2325 P		1384	345	K244				
		POS	SX	2365 P		959	420	K244				
		POS	DX	81Z1 P		738	1000	K216				
		POS	SX	82Z1 P		973	300	K129	K712			
		POS	SX	83Z1 P 1 ^A		973	300	K129	K712			
			SX	2 ^A		1528	200					
		POS	SX	86Z1 P		1328	350	K783				
		POS	SX	86Z2 P		1165	400	K783				
		POS	SX	86Z3 P		984	450	K783				
		POS	SX	86Z4 P		681	500	K783				
6-80	6.1	POS	SX	2313 P 1 ^A		1290	345	K244				
			SX	2 ^A		1290	345					
		POS	SX	2314 P 1 ^A		894	420	K244				
			SX	2 ^A		894	420					
		POS	SX	2325 P		1290	345	K244				
		POS	SX	2365 P		894	420	K244				
		POS	DX	81Z1 P		688	1000	K216				
		POS	SX	82Z1 P		907	300	K129	K712			
		POS	SX	83Z1 P 1 ^A		907	300	K129	K712			
			SX	2 ^A		1425	200					
		POS	SX	86Z1 P		1238	350	K783				
		POS	SX	86Z2 P		1086	400	K783				
		POS	SX	86Z3 P		917	450	K783				
		POS	SX	86Z4 P		635	500	K783				



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

Z.F.

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sens de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapter mntg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes
				VELsu	VELno		STD	SE/R				
6-80 6.7	POS	SX	2313 P 1 ^A		1162	345	K244					
		SX	2 ^A		1162	345						
	POS	SX	2314 P 1 ^A		806	420	K244					
		SX	2 ^A		806	420						
	POS	SX	2325 P		1162	345	K244					
	POS	SX	2365 P		806	420	K244					
	POS	DX	81Z1 P		620	1000	K216					
	POS	SX	82Z1 P		817	300	K129	K712				
	POS	SX	83Z1 P 1 ^A		817	300	K129	K712				
		SX	2 ^A		1284	200						
	POS	SX	86Z1 P		1116	350	K783					
	POS	SX	86Z2 P		978	400	K783					
	POS	SX	86Z3 P		826	450	K783					
POS	SX	86Z4 P		572	500	K783						
6-80 6.9	POS	SX	2313 P 1 ^A		966	345	K244					
		SX	2 ^A		966	345						
	POS	SX	2314 P 1 ^A		670	420	K244					
		SX	2 ^A		670	420						
	POS	SX	2325 P		966	345	K244					
	POS	SX	2365 P		670	420	K244					
	POS	DX	81Z1 P		515	1000	K216					
	POS	SX	82Z1 P		679	300	K129	K712				
	POS	SX	83Z1 P 1 ^A		679	300	K129	K712				
		SX	2 ^A		1067	200						
	POS	SX	86Z1 P		927	350	K783					
	POS	SX	86Z2 P		813	400	K783					
	POS	SX	86Z3 P		686	450	K783					
POS	SX	86Z4 P		475	500	K783						
6-80 7.9	POS	SX	2313 P 1 ^A		984	345	K244					
		SX	2 ^A		984	345						
	POS	SX	2314 P 1 ^A		682	420	K244					
		SX	2 ^A		682	420						
	POS	SX	2325 P		984	345	K244					
	POS	SX	2365 P		682	420	K244					
	POS	DX	81Z1 P		525	1000	K216					
	POS	SX	82Z1 P		692	300	K129	K712				
	POS	SX	83Z1 P 1 ^A		692	300	K129	K712				
		SX	2 ^A		1087	200						
	POS	SX	86Z1 P		945	350	K783					
	POS	SX	86Z2 P		828	400	K783					
	POS	SX	86Z3 P		700	450	K783					
POS	SX	86Z4 P		485	500	K783						
6-80 7.35	POS	SX	2313 P 1 ^A		1035	345	K244					
		SX	2 ^A		1035	345						
	POS	SX	2314 P 1 ^A		718	420	K244					
		SX	2 ^A		718	420						
	POS	SX	2325 P		1035	345	K244					
	POS	SX	2365 P		718	420	K244					
	POS	DX	81Z1 P		552	1000	K216					
POS	SX	82Z1 P		728	300	K129	K712					



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

Z.F.

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sens de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapter mntg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes
				VELsu	VELno		STD	SE/R				
					POS		SX	83Z1 P 1 ^A				
		SX	2 ^A		1143	200						
	POS	SX	86Z1 P		994	350	K783					
	POS	SX	86Z2 P		871	400	K783					
	POS	SX	86Z3 P		736	450	K783					
	POS	SX	86Z4 P		509	500	K783					
6-80	7.41	POS	SX	2313 P 1 ^A		1056	345	K244				
		SX	2 ^A		1056	345						
		POS	SX	2314 P 1 ^A		732	420	K244				
		SX	2 ^A		732	420						
		POS	SX	2325 P		1056	345	K244				
		POS	SX	2365 P		732	420	K244				
		POS	DX	81Z1 P		563	1000	K216				
		POS	SX	82Z1 P		742	300	K129	K712			
		POS	SX	83Z1 P 1 ^A		742	300	K129	K712			
		SX	2 ^A		1166	200						
		POS	SX	86Z1 P		1013	350	K783				
		POS	SX	86Z2 P		888	400	K783				
		POS	SX	86Z3 P		750	450	K783				
		POS	SX	86Z4 P		520	500	K783				
6-80	7.67	POS	SX	2313 P 1 ^A		1022	345	K244				
		SX	2 ^A		1022	345						
		POS	SX	2314 P 1 ^A		708	420	K244				
		SX	2 ^A		708	420						
		POS	SX	2325 P		1022	345	K244				
		POS	SX	2365 P		708	420	K244				
		POS	DX	81Z1 P		545	1000	K216				
		POS	SX	82Z1 P		718	300	K129	K712			
		POS	SX	83Z3 P 1 ^A		718	300	K131	K710			43
		SX	2 ^A		1129	200						
		POS	SX	86Z1 P		981	350	K783				
		POS	SX	86Z2 P		860	400	K783				
		POS	SX	86Z3 P		726	450	K783				
		POS	SX	86Z4 P		503	500	K783				
6-80	9	POS	SX	2313 P 1 ^A		872	345	K244				
		SX	2 ^A		872	345						
		POS	SX	2314 P 1 ^A		604	420	K244				
		SX	2 ^A		604	420						
		POS	SX	2325 P		872	345	K244				
		POS	SX	2365 P		604	420	K244				
		POS	DX	81Z1 P		465	1000	K216				
		POS	SX	82Z1 P		613	300	K129	K712			
		POS	SX	83Z1 P 1 ^A		613	300	K129	K712			
		SX	2 ^A		963	200						
		POS	SX	86Z1 P		837	350	K783				
		POS	SX	86Z2 P		734	400	K783				
		POS	SX	86Z3 P		620	450	K783				
		POS	SX	86Z4 P		429	500	K783				
6-80+GV80/5.3	6.7	POS	SX	2313 P 1 ^A	1470	1162	345	K244				
		SX	2 ^A		1470	1162	345					



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

Z.F.

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sens de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapt. mntg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes
				VELsu	VELno		STD	SE/R				
					POS		SX	2314 P 1 ^A				
		SX	2 ^A	1019	806	420						
	POS	SX	2325 P	1470	1162	345	K244					
	POS	SX	2365 P	1019	806	420	K244					
	POS	DX	81Z1 P	784	620	1000	K216					
	POS	SX	82Z1 P	1033	817	300	K129	K712				
	POS	SX	83Z1 P 1 ^A	1033	817	300	K129	K712				
		SX	2 ^A	1624	1284	200						
	POS	SX	86Z1 P	1411	1116	350	K783					
	POS	SX	86Z2 P	1237	978	400	K783					
	POS	SX	86Z3 P	1045	826	450	K783					
	POS	SX	86Z4 P	724	572	500	K783					
6-80+GV80/5.3	9	POS	SX	2313 P 1 ^A	1478	872	345	K244				
		SX	2 ^A	1478	872	345						
	POS	SX	2314 P 1 ^A	1024	604	420	K244					
		SX	2 ^A	1024	604	420						
	POS	SX	2325 P	1478	872	345	K244					
	POS	SX	2365 P	1024	604	420	K244					
	POS	DX	81Z1 P	788	465	1000	K216					
	POS	SX	82Z1 P	1039	613	300	K129	K712				
	POS	SX	83Z1 P 1 ^A	1039	613	300	K129	K712				
		SX	2 ^A	1632	963	200						
	POS	SX	86Z1 P	1418	837	350	K783					
	POS	SX	86Z2 P	1243	734	400	K783					
	POS	SX	86Z3 P	1050	620	450	K783					
	POS	SX	86Z4 P	727	429	500	K783					
6-80+GV80/6.7	7.67	POS	SX	2313 P 1 ^A	1170	1022	345	K244				
		SX	2 ^A	1170	1022	345						
	POS	SX	2314 P 1 ^A	811	708	420	K244					
		SX	2 ^A	811	708	420						
	POS	SX	2325 P	1170	1022	345	K244					
	POS	SX	2365 P	811	708	420	K244					
	POS	DX	81Z1 P	624	545	1000	K216					
	POS	SX	82Z1 P	822	718	300	K129	K712				
	POS	SX	83Z1 P 1 ^A	822	718	300	K129	K712				
		SX	2 ^A	1292	1129	200						
	POS	SX	86Z1 P	1123	981	350	K783					
	POS	SX	86Z2 P	985	860	400	K783					
	POS	SX	86Z3 P	832	726	450	K783					
	POS	SX	86Z4 P	576	503	500	K783					
6-80+GV80/7.48	9	POS	SX	2313 P 1 ^A	1058	872	345	K244				
		SX	2 ^A	1058	872	345						
	POS	SX	2314 P 1 ^A	733	604	420	K244					
		SX	2 ^A	733	604	420						
	POS	SX	2325 P	1058	872	345	K244					
	POS	SX	2365 P	733	604	420	K244					
	POS	DX	81Z1 P	564	465	1000	K216					
	POS	SX	82Z1 P	743	613	300	K129	K712				
	POS	SX	83Z1 P 1 ^A	743	613	300	K129	K712				
		SX	2 ^A	1168	963	200						



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

Z.F.

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sens de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage	ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapt. mntg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes		
				VELsu	VELno							STD	SE/R
					POS							SX	86Z1 P
	POS	SX	86Z2 P	890	734	400	K783						
	POS	SX	86Z3 P	752	620	450	K783						
	POS	SX	86Z4 P	521	429	500	K783						
6-80+GV80/7.52	5.66	POS	SX	2313 P 1 ^A	1384	1042	345	K244					
				2 ^A	1384	1042	345						
		POS	SX	2314 P 1 ^A	959	723	420	K244					
				2 ^A	959	723	420						
		POS	SX	2325 P	1384	1042	345	K244					
		POS	SX	2365 P	959	723	420	K244					
		POS	DX	81Z1 P	738	556	1000	K216					
		POS	SX	82Z1 P	973	733	300	K129	K712				
		POS	SX	83Z1 P 1 ^A	973	733	300	K129	K712				
				2 ^A	1528	1151	200						
		POS	SX	86Z1 P	1328	1001	350	K783					
		POS	SX	86Z2 P	1165	877	400	K783					
		POS	SX	86Z3 P	984	741	450	K783					
		POS	SX	86Z4 P	681	513	500	K783					
6-80+GV80/7.52	9	POS	SX	2313 P 1 ^A	1042	872	345	K244					
				2 ^A	1042	872	345						
		POS	SX	2314 P 1 ^A	723	604	420	K244					
				2 ^A	723	604	420						
		POS	SX	2325 P	1042	872	345	K244					
		POS	SX	2365 P	723	604	420	K244					
		POS	DX	81Z1 P	556	465	1000	K216					
		POS	SX	82Z1 P	733	613	300	K129	K712				
		POS	SX	83Z1 P 1 ^A	733	613	300	K129	K712				
				2 ^A	1151	963	200						
		POS	SX	86Z1 P	1001	837	350	K783					
		POS	SX	86Z2 P	877	734	400	K783					
		POS	SX	86Z3 P	741	620	450	K783					
		POS	SX	86Z4 P	513	429	500	K783					
6-90	5.67	POS	SX	2313 P 1 ^A		1406	345	K246					
				2 ^A		1406	345						
		POS	SX	2314 P 1 ^A		975	420	K246					
				2 ^A		975	420						
		POS	SX	2325 P		1406	345	K246					
		POS	SX	2365 P		975	420	K246					
		POS	DX	81Z1 P		750	1000	K219					
		POS	SX	82Z1 P		988	300	K131	K710				
		POS	SX	83Z1 P 1 ^A		988	300	K131	K710				
				2 ^A		1553	200						
		POS	SX	86Z1 P		1350	350	K781					
		POS	SX	86Z2 P		1184	400	K781					
		POS	SX	86Z3 P		1000	450	K781					
		POS	SX	86Z4 P		692	500	K781					
6-90	5.74	POS	SX	2313 P 1 ^A		1388	345	K246					
				2 ^A		1388	345						
		POS	SX	2314 P 1 ^A		962	420	K246					
				2 ^A		962	420						



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

Z.F.

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sens de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapter mntg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes /Notes
				VELsu	VELno		STD	SE/R				
					POS		SX	2325 P				
	POS	SX	2365 P		962	420	K246					
	POS	DX	81Z1 P		740	1000	K219					
	POS	SX	82Z1 P		975	300	K131	K710				
	POS	SX	83Z1 P 1 ^A		975	300	K131	K710				
		SX	2 ^A		1533	200						
	POS	SX	86Z1 P		1332	350	K781					
	POS	SX	86Z2 P		1168	400	K781					
	POS	SX	86Z3 P		986	450	K781					
	POS	SX	86Z4 P		683	500	K781					
6-90	6.37	POS	SX	2313 P 1 ^A		1238	345	K246				
			SX	2 ^A		1238	345					
		POS	SX	2314 P 1 ^A		858	420	K246				
			SX	2 ^A		858	420					
		POS	SX	2325 P		1238	345	K246				
		POS	SX	2365 P		858	420	K246				
		POS	DX	81Z1 P		660	1000	K219				
		POS	SX	82Z1 P		870	300	K131	K710			
		POS	SX	83Z1 P 1 ^A		870	300	K131	K710			
			SX	2 ^A		1367	200					
		POS	SX	86Z1 P		1188	350	K781				
		POS	SX	86Z2 P		1041	400	K781				
		POS	SX	86Z3 P		880	450	K781				
		POS	SX	86Z4 P		609	500	K781				
6-90	6.98	POS	SX	2313 P 1 ^A		1148	345	K246				
			SX	2 ^A		1148	345					
		POS	SX	2314 P 1 ^A		796	420	K246				
			SX	2 ^A		796	420					
		POS	SX	2325 P		1148	345	K246				
		POS	SX	2365 P		796	420	K246				
		POS	DX	81Z1 P		612	1000	K219				
		POS	SX	82Z1 P		807	300	K131	K710			
		POS	SX	83Z1 P 1 ^A		807	300	K131	K710			
			SX	2 ^A		1267	200					
		POS	SX	86Z1 P		1102	350	K781				
		POS	SX	86Z2 P		966	400	K781				
		POS	SX	86Z3 P		816	450	K781				
		POS	SX	86Z4 P		565	500	K781				
6-90	7.03	POS	SX	2313 P 1 ^A		1134	345	K246				
			SX	2 ^A		1134	345					
		POS	SX	2314 P 1 ^A		786	420	K246				
			SX	2 ^A		786	420					
		POS	SX	2325 P		1134	345	K246				
		POS	SX	2365 P		786	420	K246				
		POS	DX	81Z1 P		605	1000	K219				
		POS	SX	82Z1 P		797	300	K131	K710			
		POS	SX	83Z1 P 1 ^A		797	300	K131	K710			
			SX	2 ^A		1253	200					
		POS	SX	86Z1 P		1089	350	K781				
		POS	SX	86Z2 P		955	400	K781				



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

Z.F.

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sens de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapter mtg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes /Notes
				VELsu	VELno		STD	SE/R				
					POS		SX	86Z3 P				
	POS	SX	86Z4 P		558	500	K781					
6-90	7.4	POS	SX	2313 P 1 ^A	1078	345	K246					
				2 ^A	1078	345						
		POS	SX	2314 P 1 ^A	748	420	K246					
				2 ^A	748	420						
		POS	SX	2325 P	1078	345	K246					
		POS	SX	2365 P	748	420	K246					
		POS	DX	81Z1 P	575	1000	K219					
		POS	SX	82Z1 P	758	300	K131	K710				
		POS	SX	83Z1 P 1 ^A	758	300	K131	K710				
				2 ^A	1191	200						
		POS	SX	86Z1 P	1035	350	K781					
		POS	SX	86Z2 P	907	400	K781					
		POS	SX	86Z3 P	766	450	K781					
		POS	SX	86Z4 P	531	500	K781					
6-90	8.68	POS	SX	2313 P 1 ^A	1134	345	K246					
				2 ^A	1134	345						
		POS	SX	2314 P 1 ^A	786	420	K246					
				2 ^A	786	420						
		POS	SX	2325 P	1134	345	K246					
		POS	SX	2365 P	786	420	K246					
		POS	DX	81Z1 P	605	1000	K219					
		POS	SX	82Z1 P	797	300	K131	K710				
		POS	SX	83Z1 P 1 ^A	797	300	K131	K710				
				2 ^A	1253	200						
		POS	SX	86Z1 P	1089	350	K781					
		POS	SX	86Z2 P	955	400	K781					
		POS	SX	86Z3 P	806	450	K781					
		POS	SX	86Z4 P	558	500	K781					
6-90	9.01	POS	SX	2313 P 1 ^A	885	345	K246					
				2 ^A	885	345						
		POS	SX	2314 P 1 ^A	614	420	K246					
				2 ^A	614	420						
		POS	SX	2325 P	885	345	K246					
		POS	SX	2365 P	614	420	K246					
		POS	DX	81Z1 P	472	1000	K219					
		POS	SX	82Z1 P	622	300	K131	K710				
		POS	SX	83Z1 P 1 ^A	622	300	K131	K710				
				2 ^A	978	200						
		POS	SX	86Z1 P	850	350	K781					
		POS	SX	86Z2 P	745	400	K781					
		POS	SX	86Z3 P	629	450	K781					
		POS	SX	86Z4 P	436	500	K781					
6-90+GV90/5.67	7.03	POS	SX	2313 P 1 ^A	1406	1134	345	K246				
				2 ^A	1406	1134	345					
		POS	SX	2314 P 1 ^A	975	786	420	K246				
				2 ^A	975	786	420					
		POS	SX	2325 P	1406	1134	345	K246				
		POS	SX	2365 P	975	786	420	K246				

I dati riportati non sono vincolanti e possono subire variazioni senza preavviso - Technical specifications are not binding and can be changed without notice



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

Z.F.

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sense de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapter mntg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes /Notes
				VELsu	VELno		STD	SE/R				
					POS		DX	81Z1 P				
	POS	SX	82Z1 P	988	797	300	K131	K710				
	POS	SX	83Z1 P 1 ^A	988	797	300	K131	K710				
		SX	2 ^A	1553	1253	200						
	POS	SX	86Z1 P	1350	1089	350	K781					
	POS	SX	86Z2 P	1184	955	400	K781					
	POS	SX	86Z3 P	1000	806	450	K781					
	POS	SX	86Z4 P	692	558	500	K781					
6-90+GV90/5.74	7.03	POS	SX	2313 P 1 ^A	1389	1134	345	K246				
			SX	2 ^A	1389	1134	345					
		POS	SX	2314 P 1 ^A	963	786	420	K246				
			SX	2 ^A	963	786	420					
		POS	SX	2325 P	1389	1134	345	K246				
		POS	SX	2365 P	963	786	420	K246				
		POS	DX	81Z1 P	741	605	1000	K219				
		POS	SX	82Z1 P	977	797	300	K131	K710			
		POS	SX	83Z1 P 1 ^A	977	797	300	K131	K710			
			SX	2 ^A	1535	1253	200					
		POS	SX	86Z1 P	1334	1089	350	K781				
		POS	SX	86Z2 P	1169	955	400	K781				
		POS	SX	86Z3 P	988	806	450	K781				
		POS	SX	86Z4 P	684	558	500	K781				
6-90+GV90/7.40	9.01	POS	SX	2313 P 1 ^A	1072	885	345	K246				
			SX	2 ^A	1072	885	345					
		POS	SX	2314 P 1 ^A	744	614	420	K246				
			SX	2 ^A	744	614	420					
		POS	SX	2325 P	1072	885	345	K246				
		POS	SX	2365 P	744	614	420	K246				
		POS	DX	81Z1 P	572	472	1000	K219				
		POS	SX	82Z1 P	754	622	300	K131	K710			
		POS	SX	83Z1 P 1 ^A	754	622	300	K131	K710			
			SX	2 ^A	1185	978	200					
		POS	SX	86Z1 P	1030	850	350	K781				
		POS	SX	86Z2 P	903	745	400	K781				
		POS	SX	86Z3 P	762	629	450	K781				
		POS	SX	86Z4 P	528	436	500	K781				
8 S 109	11.35	POS	SX	2300 P 1 ^A	1744		345	K740		601K5430000		
			SX	2 ^A	1744		345					
		POS	SX	2310 P 1 ^A	1209		420	K740		601K5430000		
			SX	2 ^A	1209		420					
		POS	SX	2325 P	1744		345	K740		601K5430000		
		POS	SX	2365 P	1209		420	K740		601K5430000		
		POS	DX	81Z1 P	930		1000	K700		601K5430000		
		POS	SX	82Z1 P	1226		300	K701	K702	601K5430000		
		POS	SX	83Z1 P 1 ^A	1226		300	K701	K702	601K5430000		
			SX	2 ^A	1926		200					
		POS	SX	86Z1 P	1674		350	K785		601K5430000		
		POS	SX	86Z2 P	1468		400	K785		601K5430000		
		POS	SX	86Z3 P	1240		450	K785		601K5430000		
		POS	SX	86Z4 P	858		500	K785		601K5430000		

70



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

Z.F.

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sens de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapter mntg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes
				VELsu	VELno		STD	SE/R				
9S75 9.56	POS	SX	2300 P 1 ^A		1594	345	K740		601K5420000			
		SX	2 ^A		1594	345						
	POS	SX	2310 P 1 ^A		1105	420	K740		601K5420000			
		SX	2 ^A		1105	420						
	POS	SX	2325 P		1594	345	K740		601K5420000			
	POS	SX	2365 P		1105	420	K740		601K5420000			
	POS	DX	81Z1 P		850	1000	K700		601K5420000			74
	POS	SX	82Z1 P		1120	300	K701	K702	601K5420000			
	POS	SX	83Z1 P 1 ^A		1120	300	K701	K702	601K5420000			
		SX	2 ^A		1760	200						
	POS	SX	86Z1 P		1530	350	K785		601K5420000			
	POS	SX	86Z2 P		1341	400	K785		601K5420000			
	POS	SX	86Z3 P		1133	450	K785		601K5420000			
POS	SX	86Z4 P		785	500	K785		601K5420000				
9S75 13.16	POS	SX	2300 P 1 ^A		1162	345	K740		601K5420000			
		SX	2 ^A		1162	345						
	POS	SX	2310 P 1 ^A		806	420	K740		601K5420000			
		SX	2 ^A		806	420						
	POS	SX	2325 P		1162	345	K740		601K5420000			
	POS	SX	2365 P		806	420	K740		601K5420000			
	POS	DX	81Z1 P		620	1000	K700		601K5420000			74
	POS	SX	82Z1 P		817	300	K701	K702	601K5420000			
	POS	SX	83Z1 P 1 ^A		817	300	K701	K702	601K5420000			
		SX	2 ^A		1284	200						
	POS	SX	86Z1 P		1116	350	K785		601K5420000			
	POS	SX	86Z2 P		978	400	K785		601K5420000			
	POS	SX	86Z3 P		826	450	K785		601K5420000			
POS	SX	86Z4 P		572	500	K785		601K5420000				
9S109 10.24	POS	SX	2300 P 1 ^A		1444	345	K740		601K5350000			
		SX	2 ^A		1444	345						
	POS	SX	2310 P 1 ^A		1001	420	K740		601K5350000			
		SX	2 ^A		1001	420						
	POS	SX	2325 P		1444	345	K740		601K5350000			
	POS	SX	2365 P		1001	420	K740		601K5350000			
	POS	DX	81Z1 P		770	1000	K700		601K5350000			70
	POS	SX	82Z1 P		1015	300	K701	K702	601K5350000			
	POS	SX	83Z1 P 1 ^A		1015	300	K701	K702	601K5350000			
		SX	2 ^A		1595	200						
	POS	SX	86Z1 P		1386	350	K785		601K5350000			
	POS	SX	86Z2 P		1215	400	K785		601K5350000			
	POS	SX	86Z3 P		1026	450	K785		601K5350000			
POS	SX	86Z4 P		711	500	K785		601K5350000				
9S109 12.91	POS	SX	2300 P 1 ^A		1350	345	K740		601K5410000			
		SX	2 ^A		1350	345						
	POS	SX	2310 P 1 ^A		936	420	K740		601K5410000			
		SX	2 ^A		936	420						
	POS	SX	2325 P		1350	345	K740		601K5410000			
	POS	SX	2365 P		936	420	K740		601K5410000			
	POS	DX	81Z1 P		720	1000	K700		601K5410000			70
POS	SX	82Z1 P		949	300	K701	K702	601K5410000				



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

Z.F.

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sens de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapter mntg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes
				VELsu	VELno		STD	SE/R				
	POS	SX	83Z1 P 1 ^A		949	300	K701	K702	601K5410000			
		SX	2 ^A		1491	200						
	POS	SX	86Z1 P		1296	350	K785		601K5410000			
	POS	SX	86Z2 P		1136	400	K785		601K5410000			
	POS	SX	86Z3 P		960	450	K785		601K5410000			
	POS	SX	86Z4 P		665	500	K785		601K5410000			
9S109	12.92	POS	SX	2300 P 1 ^A		1350	345	K740		601K5430000		
			SX	2 ^A		1350	345					
		POS	SX	2310 P 1 ^A		936	420	K740		601K5430000		
			SX	2 ^A		936	420					
		POS	SX	2325 P		1350	345	K740		601K5430000		
		POS	SX	2365 P		936	420	K740		601K5430000		
		POS	DX	81Z1 P		720	1000	K700		601K5430000		70
		POS	SX	82Z1 P		949	300	K701	K702	601K5430000		
		POS	SX	83Z1 P 1 ^A		949	300	K701	K702	601K5430000		
			SX	2 ^A		1491	200					
		POS	SX	86Z1 P		1296	350	K785		601K5430000		
		POS	SX	86Z2 P		1136	400	K785		601K5430000		
		POS	SX	86Z3 P		960	450	K785		601K5430000		
		POS	SX	86Z4 P		665	500	K785		601K5430000		
16K130	10.14	POS	SX	2300 P 1 ^A	1806	1538	345	K488		601K5470000		
			SX	2 ^A	1806	1538	345					
		POS	SX	2310 P 1 ^A	1252	1066	420	K488		601K5470000		
			SX	2 ^A	1252	1066	420					
		POS	SX	2325 P	1806	1538	345	K488		601K5470000		
		POS	SX	2365 P	1252	1066	420	K488		601K5470000		
		POS	DX	81Z1 P	963	820	1000	K219		601K5470000		
		POS	SX	82Z1 P	1269	1081	300	K131	K710	601K5470000		
		POS	SX	83Z1 P 1 ^A	1269	1081	300	K131	K710	601K5470000		
			SX	2 ^A	1994	1698	200					
		POS	SX	86Z1 P	1733	1476	350	K781		601K5470000		81
		POS	SX	86Z2 P	1520	1294	400	K781		601K5470000		81
		POS	SX	86Z3 P	1284	1093	450	K781		601K5470000		81
		POS	SX	86Z4 P	889	757	500	K781		601K5470000		81
16K130	11.46	POS	SX	2300 P 1 ^A	1806	1538	345	K488		601K5470000		
16K130	13.85		SX	2 ^A	1806	1538	345					
		POS	SX	2310 P 1 ^A	1252	1066	420	K488		601K5470000		
			SX	2 ^A	1252	1066	420					
		POS	SX	2325 P	1806	1538	345	K488		601K5470000		
		POS	SX	2365 P	1252	1066	420	K488		601K5470000		
		POS	DX	81Z1 P	963	820	1000	K219		601K5470000		
		POS	SX	82Z1 P	1269	1081	300	K131	K710	601K5470000		
		POS	SX	83Z1 P 1 ^A	1269	1081	300	K131	K710	601K5470000		
			SX	2 ^A	1994	1698	200					
		POS	SX	86Z1 P	1733	1476	350	K781		601K5470000		81
		POS	SX	86Z2 P	1520	1294	400	K781		601K5470000		81
		POS	SX	86Z3 P	1284	1093	450	K781		601K5470000		81
		POS	SX	86Z4 P	889	757	500	K781		601K5470000		81
16K130	13.68	POS	SX	2300 P 1 ^A	1806	1538	345	K488		601K5470000		
			SX	2 ^A	1806	1538	345					



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

Z.F.

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sens de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapt. mntg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes
				VELsu	VELno		STD	SE/R				
	POS	SX	2310 P 1 ^A	1252	1066	420	K488		601K5470000			
		SX	2 ^A	1252	1066	420						
	POS	SX	2325 P	1806	1538	345	K488		601K5470000			
	POS	SX	2365 P	1252	1066	420	K488		601K5470000			
	POS	DX	81Z1 P	963	820	1000	K219		601K5470000			
	POS	SX	82Z1 P	1269	1081	300	K131	K710	601K5470000			
	POS	SX	83Z1 P 1 ^A	1269	1081	300	K131	K710	601K5470000			
		SX	2 ^A	1994	1698	200						
	POS	SX	86Z1 P	1733	1476	350	K781		601K5470000			81
	POS	SX	86Z2 P	1520	1294	400	K781		601K5470000			81
	POS	SX	86Z3 P	1284	1093	450	K781		601K5470000			81
	POS	SX	86Z4 P	889	757	500	K781		601K5470000			81
16K130	14.29	POS	SX	2300 P 1 ^A	1706	1388	345	K488		601K5460000		
16K130	17.28		SX	2 ^A	1706	1388	345					
16S130	14.29	POS	SX	2310 P 1 ^A	1183	962	420	K488		601K5460000		
16S130	17.28		SX	2 ^A	1183	962	420					
16S160	14.29	POS	SX	2325 P	1706	1388	345	K488		601K5460000		
16S160	17.06	POS	SX	2365 P	1183	962	420	K488		601K5460000		
16S160	17.28	POS	DX	81Z1 P	910	740	1000	K219		601K5460000		
16S190	17.06	POS	SX	82Z1 P	1199	975	300	K131	K710	601K5460000		
		POS	SX	83Z1 P 1 ^A	1199	975	300	K131	K710	601K5460000		
			SX	2 ^A	1885	1533	200					
		POS	SX	86Z1 P	1638	1332	350	K781		601K5460000		81
		POS	SX	86Z2 P	1436	1168	400	K781		601K5460000		81
		POS	SX	86Z3 P	1213	986	450	K781		601K5460000		81
		POS	SX	86Z4 P	840	683	500	K781		601K5460000		81
16S109	11.86	POS	SX	2300 P 1 ^A	1650	1406	345	K740		601K5350000		
			SX	2 ^A	1650	1406	345					
		POS	SX	2310 P 1 ^A	1144	975	420	K740		601K5350000		
			SX	2 ^A	1144	975	420					
		POS	SX	2325 P	1650	1406	345	K740		601K5350000		
		POS	SX	2365 P	1144	975	420	K740		601K5350000		
		POS	DX	81Z1 P	880	750	1000	K700		601K5350000		70
		POS	SX	82Z1 P	1160	988	300	K701	K702	601K5350000		
		POS	SX	83Z1 P 1 ^A	1160	988	300	K701	K702	601K5350000		
			SX	2 ^A	1822	1553	200					
		POS	SX	86Z1 P	1584	1350	350	K785		601K5350000		
		POS	SX	86Z2 P	1389	1184	400	K785		601K5350000		
		POS	SX	86Z3 P	1173	1000	450	K785		601K5350000		
		POS	SX	86Z4 P	812	692	500	K785		601K5350000		
16S109	13.3	POS	SX	2300 P 1 ^A	1744	1481	345	K740		601K5430000		
16S109	13.42		SX	2 ^A	1744	1481	345					
		POS	SX	2310 P 1 ^A	1209	1027	420	K740		601K5430000		
			SX	2 ^A	1209	1027	420					
		POS	SX	2325 P	1744	1481	345	K740		601K5430000		
		POS	SX	2365 P	1209	1027	420	K740		601K5430000		
		POS	DX	81Z1 P	930	790	1000	K700		601K5430000		70
		POS	SX	82Z1 P	1226	1041	300	K701	K702	601K5430000		
		POS	SX	83Z1 P 1 ^A	1226	1041	300	K701	K702	601K5430000		
			SX	2 ^A	1926	1636	200					



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

Z.F.

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sens de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapter mtg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes
				VELsu	VELno		STD	SE/R				
	POS	SX	86Z1 P	1674	1422	350	K785		601K5430000			
	POS	SX	86Z2 P	1468	1247	400	K785		601K5430000			
	POS	SX	86Z3 P	1240	1053	450	K785		601K5430000			
	POS	SX	86Z4 P	858	729	500	K785		601K5430000			
16S109	13.31	POS	SX	2300 P 1 ^A	1744	1481	345	K740		601K5410000		
16S109	13.41			2 ^A	1744	1481	345					
		POS	SX	2310 P 1 ^A	1209	1027	420	K740		601K5410000		
				2 ^A	1209	1027	420					
		POS	SX	2325 P	1744	1481	345	K740		601K5410000		
		POS	SX	2365 P	1209	1027	420	K740		601K5410000		
		POS	DX	81Z1 P	930	790	1000	K700		601K5410000		70
		POS	SX	82Z1 P	1226	1041	300	K701	K702	601K5410000		
		POS	SX	83Z1 P 1 ^A	1226	1041	300	K701	K702	601K5410000		
				2 ^A	1926	1636	200					
		POS	SX	86Z1 P	1674	1422	350	K785		601K5410000		
		POS	SX	86Z2 P	1468	1247	400	K785		601K5410000		
		POS	SX	86Z3 P	1240	1053	450	K785		601K5410000		
		POS	SX	86Z4 P	858	729	500	K785		601K5410000		
16S109	13.53	POS	SX	2300 P 1 ^A	1706	1406	345	K740		601K5350000		
				2 ^A	1706	1406	345					
		POS	SX	2310 P 1 ^A	1183	975	420	K740		601K5350000		
				2 ^A	1183	975	420					
		POS	SX	2325 P	1706	1406	345	K740		601K5350000		
		POS	SX	2365 P	1183	975	420	K740		601K5350000		
		POS	DX	81Z1 P	910	750	1000	K700		601K5350000		70
		POS	SX	82Z1 P	1199	988	300	K701	K702	601K5350000		
		POS	SX	83Z1 P 1 ^A	1199	988	300	K701	K702	601K5350000		
				2 ^A	1885	1553	200					
		POS	SX	86Z1 P	1638	1350	350	K785		601K5350000		
		POS	SX	86Z2 P	1436	1184	400	K785		601K5350000		
		POS	SX	86Z3 P	1213	1000	450	K785		601K5350000		
		POS	SX	86Z4 P	840	692	500	K785		601K5350000		
16S112	11.46	POS	SX	2300 P 1 ^A	1806	1538	345	K488		601K5470000		
16S112	13.68			2 ^A	1806	1538	345					
16S112	13.85	POS	SX	2310 P 1 ^A	1252	1066	420	K488		601K5470000		
				2 ^A	1252	1066	420					
		POS	SX	2325 P	1806	1538	345	K488		601K5470000		
		POS	SX	2365 P	1252	1066	420	K488		601K5470000		
		POS	DX	81Z1 P	963	820	1000	K219		601K5470000		
		POS	SX	82Z1 P	1269	1081	300	K131	K710	601K5470000		
		POS	SX	83Z1 P 1 ^A	1269	1081	300	K131	K710	601K5470000		
				2 ^A	1994	1698	200					
		POS	SX	86Z1 P	1733	1476	350	K781		601K5470000		
		POS	SX	86Z2 P	1520	1294	400	K781		601K5470000		
		POS	SX	86Z3 P	1284	1093	450	K781		601K5470000		
		POS	SX	86Z4 P	889	757	500	K781		601K5470000		
16S112	17.28	POS	SX	2300 P 1 ^A	1706	1388	345	K488		601K5460000		
				2 ^A	1706	1388	345					
		POS	SX	2310 P 1 ^A	1183	962	420	K488		601K5460000		
				2 ^A	1183	962	420					



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

Z.F.

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sens de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapter mntg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes /Notes
				VELsu	VELno		STD	SE/R				
	POS	SX	2325 P	1706	1388	345	K488		601K5460000			
	POS	SX	2365 P	1183	962	420	K488		601K5460000			
	POS	DX	81Z1 P	910	740	1000	K219		601K5460000			
	POS	SX	82Z1 P	1199	975	300	K131	K710	601K5460000			
	POS	SX	83Z1 P 1 ^A	1199	975	300	K131	K710	601K5460000			
		SX	2 ^A	1885	1533	200						
	POS	SX	86Z1 P	1638	1332	350	K781		601K5460000			
	POS	SX	86Z2 P	1436	1168	400	K781		601K5460000			
	POS	SX	86Z3 P	1213	986	450	K781		601K5460000			
	POS	SX	86Z4 P	840	683	500	K781		601K5460000			
16S130	10.14	POS	SX	2300 P 1 ^A	1806	1538	345	K488		601K5460000		
16S130	11.46		SX	2 ^A	1806	1538	345					
16S130	13.68	POS	SX	2310 P 1 ^A	1252	1066	420	K488		601K5460000		
16S130	13.85		SX	2 ^A	1252	1066	420					
16S160	11.46	POS	SX	2325 P	1806	1538	345	K488		601K5460000		
16S160	13.68	POS	SX	2365 P	1252	1066	420	K488		601K5460000		
16S160	13.85	POS	DX	81Z1 P	963	820	1000	K219		601K5460000		
16S190	11.46	POS	SX	82Z1 P	1269	1081	300	K131	K710	601K5460000		
16S190	13.68	POS	SX	83Z1 P 1 ^A	1269	1081	300	K131	K710	601K5460000		
16S220	13.68		SX	2 ^A	1994	1698	200					
		POS	SX	86Z1 P	1733	1476	350	K781		601K5460000		81
		POS	SX	86Z2 P	1520	1294	400	K781		601K5460000		81
		POS	SX	86Z3 P	1284	1093	450	K781		601K5460000		81
		POS	SX	86Z4 P	889	757	500	K781		601K5460000		81
16S150	13.8	POS	SX	2300 P 1 ^A	1725	1444	345	K488		601K5470000		
16S150	16.47		SX	2 ^A	1725	1444	345					
		POS	SX	2310 P 1 ^A	1196	1001	420	K488		601K5470000		
			SX	2 ^A	1196	1001	420					
		POS	SX	2325 P	1725	1444	345	K488		601K5470000		
		POS	SX	2365 P	1196	1001	420	K488		601K5470000		
		POS	DX	81Z1 P	920	770	1000	K219		601K5470000		
		POS	SX	82Z1 P	1213	1015	300	K131	K710	601K5470000		
		POS	SX	83Z1 P 1 ^A	1213	1015	300	K131	K710	601K5470000		
			SX	2 ^A	1905	1595	200					
		POS	SX	86Z1 P	1656	1386	350	K781		601K5470000		81
		POS	SX	86Z2 P	1452	1215	400	K781		601K5470000		81
		POS	SX	86Z3 P	1226	1026	450	K781		601K5470000		81
		POS	SX	86Z4 P	849	711	500	K781		601K5470000		81
16S150 IT	13.8	POS	SX	2300 P 1 ^A	1725	1444	345	K301		601K5480000		
			SX	2 ^A	1725	1444	345					
		POS	SX	2310 P 1 ^A	1196	1001	420	K301		601K5480000		
			SX	2 ^A	1196	1001	420					
		POS	SX	2325 P	1725	1444	345	K301		601K5480000		
		POS	SX	2365 P	1196	1001	420	K301		601K5480000		
		POS	DX	81Z1 P	920	770	1000	K302		601K5480000		
		POS	SX	82Z1 P	1213	1015	300	K241	K240	601K5480000		
		POS	SX	83Z1 P 1 ^A	1213	1015	300	K241	K240	601K5480000		
			SX	2 ^A	1905	1595	200					
		POS	SX	86Z1 P	1656	1386	350	K784		601K5480000		
		POS	SX	86Z2 P	1452	1215	400	K784		601K5480000		



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

Z.F.

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sense de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapter mto. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes
				VELsu	VELno		STD	SE/R				
	POS	SX	86Z3 P	1226	1026	450	K784		601K5480000			
	POS	SX	86Z4 P	849	711	500	K784		601K5480000			
16S151 (OLD) 13.8	POS	SX	1865 P	1196	1001	420	K290		601K5160000			
16S151 (OLD) 13.85	POS	SX	2300 P 1 ^A	1725	1444	345	K246		601K5460000			71
16S151 (OLD) 16.47		SX	2 ^A	1725	1444	345						
16S151 (OLD) 16.53	POS	SX	2310 P 1 ^A	1196	1001	420	K246		601K5460000			71
16S221 (OLD) 13.8		SX	2 ^A	1196	1001	420						
16S221 (OLD) 13.85	POS	SX	2325 P	1725	1444	345	K246		601K5460000			71
16S221 (OLD) 16.47	POS	SX	2365 P	1196	1001	420	K246		601K5460000			71
16S221 (OLD) 16.53	POS	DX	81Z1 P	920	770	1000	K219		601K5460000			
FINO N --051011	POS	SX	82Z1 P	1213	1015	300	K131	K710	601K5460000			
	POS	SX	83Z1 P 1 ^A	1213	1015	300	K131	K710	601K5460000			
		SX	2 ^A	1905	1595	200						
	POS	SX	86Z1 P	1656	1386	350	K781		601K5460000			81
	POS	SX	86Z2 P	1452	1215	400	K781		601K5460000			81
	POS	SX	86Z3 P	1226	1026	450	K781		601K5460000			81
	POS	SX	86Z4 P	849	711	500	K781		601K5460000			81
16S151 - 0,84 13.8	POS	SX	1865 P	1196	1001	420	K290		601K5170000			
16S151/1.00 D.D 16.47	POS	SX	2300 P 1 ^A	1725	1444	345	K246		601K5360000			71
16S181/1.00 D.D 16.47		SX	2 ^A	1725	1444	345						
16S221 - 0,84 13.8	POS	SX	2310 P 1 ^A	1196	1001	420	K246		601K5360000			71
16S221 OD 0.84 13.74		SX	2 ^A	1196	1001	420						
	POS	SX	2325 P	1725	1444	345	K246		601K5360000			71
	POS	SX	2365 P	1196	1001	420	K246		601K5360000			71
	POS	SX	2565 P 1 ^A	1725	1444	345	K290		601K5170000			
		SX	2 ^A	1725	1444	345						
	POS	SX	2566 P 1 ^A	1196	1001	420	K290		601K5170000			
		SX	2 ^A	1196	1001	420						
	POS	DX	81Z1 P	920	770	1000	K219		601K5360000			
	POS	SX	82Z1 P	1213	1015	300	K131	K710	601K5360000			
	POS	SX	83Z1 P 1 ^A	1213	1015	300	K131	K710	601K5360000			
		SX	2 ^A	1905	1595	200						
	POS	SX	85ZA P 1 ^A	1111	930	800	K500		601K5570000			73
		DX	2 ^A	1570	1314	500						
	POS	SX	85ZB P 1 ^A	1111	930	800	K500		601K5570000			73
		SX	2 ^A	1111	930	800						
	POS	SX	86Z1 P	1656	1386	350	K781		601K5360000			81
	POS	SX	86Z2 P	1452	1215	400	K781		601K5360000			81
	POS	SX	86Z3 P	1226	1026	450	K781		601K5360000			81
	POS	SX	86Z4 P	849	711	500	K781		601K5360000			81
16S151 IT (OLD) 13.8	POS	SX	1865 P	1196	1001	420	K290		601K5160000			58
16S221 IT (OLD) 13.8	POS	SX	2300 P 1 ^A	1725	1444	345	K301		601K5490000			58
16S221 IT (OLD) 16.47		SX	2 ^A	1725	1444	345						
FINO N --051011	POS	SX	2310 P 1 ^A	1196	1001	420	K301		601K5490000			58
		SX	2 ^A	1196	1001	420						
	POS	SX	2325 P	1725	1444	345	K301		601K5490000			58
	POS	SX	2365 P	1196	1001	420	K301		601K5490000			58
	POS	DX	81Z1 P	920	770	1000	K302		601K5490000			
	POS	SX	82Z1 P	1213	1015	300	K241	K240	601K5490000			
	POS	SX	83Z1 P 1 ^A	1213	1015	300	K241	K240	601K5490000			



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

Z.F.

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sens de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapter mntg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes
				VELsu	VELno		STD	SE/R				
		SX	2 ^A	1905	1595	200						
	POS	SX	86Z1 P	1656	1386	350	K784		601K5480000			
	POS	SX	86Z2 P	1452	1215	400	K784		601K5480000			
	POS	SX	86Z3 P	1226	1026	450	K784		601K5480000			
	POS	SX	86Z4 P	849	711	500	K784		601K5480000			
16S151 OD 0,84	11.54	POS	SX	1865 P	1422	1196	420	K290		601K5170000		
16S151 OD 0,84	13.8	POS	SX	2300 P 1 ^A	2051	1725	345	K246		601K5360000		71
16S181 OD 0,84	11.54		SX	2 ^A	2051	1725	345					
16S181 OD 0,84	13.8	POS	SX	2310 P 1 ^A	1422	1196	420	K246		601K5360000		71
16S221 OD 0,84	11.54		SX	2 ^A	1422	1196	420					
16S221 OD 0,84	13.8	POS	SX	2325 P	2051	1725	345	K246		601K5360000		71
		POS	SX	2365 P	1422	1196	420	K246		601K5360000		71
		POS	SX	2565 P 1 ^A	2051	1725	345	K290		601K5170000		
			SX	2 ^A	2051	1725	345					
		POS	SX	2566 P 1 ^A	1422	1196	420	K290		601K5170000		
			SX	2 ^A	1422	1196	420					
		POS	DX	81Z1 P	1094	920	1000	K219		601K5360000		
		POS	SX	82Z1 P	1442	1213	300	K131	K710	601K5360000		
		POS	SX	83Z1 P 1 ^A	1442	1213	300	K131	K710	601K5360000		
			SX	2 ^A	2266	1905	200					
		POS	SX	85ZA P 1 ^A	1322	1111	800	K500		601K5570000		73
			DX	2 ^A	1866	1570	500					
		POS	SX	85ZB P 1 ^A	1322	1111	800	K500		601K5570000		73
			SX	2 ^A	1322	1111	800					
		POS	SX	86Z1 P	1969	1656	350	K781		601K5360000		81
		POS	SX	86Z2 P	1726	1452	400	K781		601K5360000		81
		POS	SX	86Z3 P	1458	1226	450	K781		601K5360000		81
		POS	SX	86Z4 P	1010	849	500	K781		601K5360000		81
16S151 OD 0,84	13.86	POS	SX	1865 P	1422	1196	420	K290		601K5170000		
16S181 OD 0,84	13.86	POS	SX	2300 P 1 ^A	2051	1725	345	K246		601K5360000		71
			SX	2 ^A	2051	1725	345					
		POS	SX	2310 P 1 ^A	1422	1196	420	K246		601K5360000		71
			SX	2 ^A	1422	1196	420					
		POS	SX	2325 P	2051	1725	345	K246		601K5360000		71
		POS	SX	2365 P	1422	1196	420	K246		601K5360000		71
		POS	SX	2565 P 1 ^A	2051	1725	345	K290		601K5170000		
			SX	2 ^A	2051	1725	345					
		POS	SX	2566 P 1 ^A	1422	1196	420	K290		601K5170000		
			SX	2 ^A	1422	1196	420					
		POS	DX	81Z1 P	1094	920	1000	K219		601K5360000		
		POS	SX	82Z1 P	1442	1213	300	K131	K710	601K5360000		
		POS	SX	83Z1 P 1 ^A	1442	1213	300	K131	K710	601K5360000		
			SX	2 ^A	2266	1905	200					
		POS	SX	85ZA P 1 ^A	1322	1111	800	K500		601K5570000		73
			DX	2 ^A	1866	1570	500					
		POS	SX	85ZB P 1 ^A	1322	1111	800	K500		601K5570000		73
			SX	2 ^A	1322	1111	800					
		POS	SX	86Z1 P	1969	1656	350	K781		601K5360000		81
		POS	SX	86Z2 P	1726	1452	400	K781		601K5360000		81
		POS	SX	86Z3 P	1458	1226	450	K781		601K5360000		81



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

Z.F.

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sense de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapter mntg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes
				VELsu	VELno		STD	SE/R				
	POS	SX	86Z4 P	1010	849	500	K781		601K5360000			81
16S151- 0,84 IT 13.8	POS	SX	1865 P	1196	1001	420	K290		601K5170000			58
16S151/1.0ITD.D 16.47	POS	SX	2300 P 1 ^A	1725	1444	345	K301		601K5370000			58
16S151OD0.84 IT 13.74		SX	2 ^A	1725	1444	345						
16S181/1.00ITDD 16.47	POS	SX	2310 P 1 ^A	1196	1001	420	K301		601K5370000			58
16S221- 0,84 IT 13.8		SX	2 ^A	1196	1001	420						
16S221OD0.84 IT 13.74	POS	SX	2325 P	1725	1444	345	K301		601K5370000			58
	POS	SX	2365 P	1196	1001	420	K301		601K5370000			58
	POS	SX	2565 P 1 ^A	1725	1444	345	K290		601K5170000			58
		SX	2 ^A	1725	1444	345						
	POS	SX	2566 P 1 ^A	1196	1001	420	K290		601K5170000			58
		SX	2 ^A	1196	1001	420						
	POS	DX	81Z1 P	920	770	1000	K302		601K5370000			
	POS	SX	82Z1 P	1213	1015	300	K241	K240	601K5370000			
	POS	SX	83Z1 P 1 ^A	1213	1015	300	K241	K240	601K5370000			
		SX	2 ^A	1905	1595	200						
	POS	SX	85ZA P 1 ^A	1111	930	800	K735		601K5570000			73
		DX	2 ^A	1570	1314	500						
	POS	SX	85ZB P 1 ^A	1111	930	800	K735		601K5570000			73
		SX	2 ^A	1111	930	800						
	POS	SX	86Z1 P	1656	1386	350	K784		601K5370000			
	POS	SX	86Z2 P	1452	1215	400	K784		601K5370000			
	POS	SX	86Z3 P	1226	1026	450	K784		601K5370000			
	POS	SX	86Z4 P	849	711	500	K784		601K5370000			
16S151/1.00 D.D 13.8	POS	SX	1865 P	1196	1001	420	K290		601K5170000			
16S151/1.00 D.D 13.74	POS	SX	2300 P 1 ^A	1725	1444	345	K246		601K5360000			71
16S151/1.00 D.D 16.41		SX	2 ^A	1725	1444	345						
16S181/1.00 D.D 13.8	POS	SX	2310 P 1 ^A	1196	1001	420	K246		601K5360000			71
16S181/1.00 D.D 16.41		SX	2 ^A	1196	1001	420						
16S221 (NEW) 16.47	POS	SX	2325 P	1725	1444	345	K246		601K5360000			71
16S221/1.00 D.D 13.8	POS	SX	2365 P	1196	1001	420	K246		601K5360000			71
16S221/1.00 D.D 16.41	POS	SX	2565 P 1 ^A	1725	1444	345	K290		601K5170000			
DA N --051111		SX	2 ^A	1725	1444	345						
	POS	SX	2566 P 1 ^A	1196	1001	420	K290		601K5170000			
		SX	2 ^A	1196	1001	420						
	POS	DX	81Z1 P	920	770	1000	K219		601K5360000			
	POS	SX	82Z1 P	1213	1015	300	K131	K710	601K5360000			
	POS	SX	83Z1 P 1 ^A	1213	1015	300	K131	K710	601K5360000			
		SX	2 ^A	1905	1595	200						
	POS	SX	85ZA P 1 ^A	1111	930	800	K500		601K5570000			73
		DX	2 ^A	1570	1314	500						
	POS	SX	85ZB P 1 ^A	1111	930	800	K500		601K5570000			73
		SX	2 ^A	1111	930	800						
	POS	SX	86Z1 P	1656	1386	350	K781		601K5360000			81
	POS	SX	86Z2 P	1452	1215	400	K781		601K5360000			81
	POS	SX	86Z3 P	1226	1026	450	K781		601K5360000			81
	POS	SX	86Z4 P	849	711	500	K781		601K5360000			81
16S151/1.0ITD.D 13.8	POS	SX	1865 P	1196	1001	420	K290		601K5170000			58
16S151/1.0ITD.D 16.41	POS	SX	2300 P 1 ^A	1725	1444	345	K301		601K5370000			58
16S181/1.00ITDD 13.8		SX	2 ^A	1725	1444	345						



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

Z.F.

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sense de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapt. mntg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes
				VELsu	VELno		STD	SE/R				
16S181/1.00ITDD 16.41	POS	SX	2310 P 1 ^A	1196	1001	420	K301		601K5370000			58
16S221 IT (NEW) 16.47		SX	2 ^A	1196	1001	420						
16S221/1.0ITD.D 13.8	POS	SX	2325 P	1725	1444	345	K301		601K5370000			58
16S221/1.0ITD.D 16.41	POS	SX	2365 P	1196	1001	420	K301		601K5370000			58
DA N --051111	POS	SX	2565 P 1 ^A	1725	1444	345	K290		601K5170000			58
		SX	2 ^A	1725	1444	345						
	POS	SX	2566 P 1 ^A	1196	1001	420	K290		601K5170000			58
		SX	2 ^A	1196	1001	420						
	POS	DX	81Z1 P	920	770	1000	K302		601K5370000			
	POS	SX	82Z1 P	1213	1015	300	K241	K240	601K5370000			
	POS	SX	83Z1 P 1 ^A	1213	1015	300	K241	K240	601K5370000			
		SX	2 ^A	1905	1595	200						
	POS	SX	85ZA P 1 ^A	1111	930	800	K735		601K5570000			73
		DX	2 ^A	1570	1314	500						
	POS	SX	85ZB P 1 ^A	1111	930	800	K735		601K5570000			73
		SX	2 ^A	1111	930	800						
	POS	SX	86Z1 P	1656	1386	350	K784		601K5370000			
	POS	SX	86Z2 P	1452	1215	400	K784		601K5370000			
	POS	SX	86Z3 P	1226	1026	450	K784		601K5370000			
	POS	SX	86Z4 P	849	711	500	K784		601K5370000			
16S151OD0,84 IT 11.54	POS	SX	1865 P	1422	1196	420	K290		601K5170000			58
16S151OD0,84 IT 13.8	POS	SX	2300 P 1 ^A	2051	1725	345	K301		601K5370000			58
16S181OD0,84 IT 11.54		SX	2 ^A	2051	1725	345						
16S181OD0,84 IT 13.8	POS	SX	2310 P 1 ^A	1422	1196	420	K301		601K5370000			58
16S221OD0,84 IT 11.54		SX	2 ^A	1422	1196	420						
16S221OD0,84 IT 13.8	POS	SX	2325 P	2051	1725	345	K301		601K5370000			58
	POS	SX	2365 P	1422	1196	420	K301		601K5370000			58
	POS	SX	2565 P 1 ^A	2051	1725	345	K290		601K5170000			58
		SX	2 ^A	2051	1725	345						
	POS	SX	2566 P 1 ^A	1422	1196	420	K290		601K5170000			58
		SX	2 ^A	1422	1196	420						
	POS	DX	81Z1 P	1094	920	1000	K302		601K5370000			
	POS	SX	82Z1 P	1442	1213	300	K241	K240	601K5370000			
	POS	SX	83Z1 P 1 ^A	1442	1213	300	K241	K240	601K5370000			
		SX	2 ^A	2266	1905	200						
	POS	SX	85ZA P 1 ^A	1322	1111	800	K735		601K5570000			73
		DX	2 ^A	1866	1570	500						
	POS	SX	85ZB P 1 ^A	1322	1111	800	K735		601K5570000			73
		SX	2 ^A	1322	1111	800						
	POS	SX	86Z1 P	1969	1656	350	K784		601K5370000			
	POS	SX	86Z2 P	1726	1452	400	K784		601K5370000			
POS	SX	86Z3 P	1458	1226	450	K784		601K5370000				
POS	SX	86Z4 P	1010	849	500	K784		601K5370000				
16S151OD0,84 IT 13.86	POS	SX	1865 P	1422	1196	420	K290		601K5170000			58
16S181OD0,84 IT 13.86	POS	SX	2300 P 1 ^A	2051	1725	345	K301		601K5370000			58
16S221OD0,84 IT 13.86		SX	2 ^A	2051	1725	345						
	POS	SX	2310 P 1 ^A	1422	1196	420	K301		601K5370000			58
		SX	2 ^A	1422	1196	420						
	POS	SX	2325 P	2051	1725	345	K301		601K5370000			58
	POS	SX	2365 P	1422	1196	420	K301		601K5370000			58



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

Z.F.

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sense de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapt. mntg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes
				VELsu	VELno		STD	SE/R				
	POS	SX	2565 P 1 ^A	2051	1725	345	K290		601K5170000			58
		SX	2 ^A	2051	1725	345						
	POS	SX	2566 P 1 ^A	1422	1196	420	K290		601K5170000			58
		SX	2 ^A	1422	1196	420						
	POS	DX	81Z1 P	1094	920	1000	K302		601K5370000			
	POS	SX	82Z1 P	1442	1213	300	K241	K240	601K5370000			
	POS	SX	83Z1 P 1 ^A	1442	1213	300	K241	K240	601K5370000			
		SX	2 ^A	2266	1905	200						
	POS	SX	85ZA P 1 ^A	1322	1111	800	K735		601K5570000			73
		DX	2 ^A	1866	1570	500						
	POS	SX	85ZB P 1 ^A	1322	1111	800	K735		601K5570000			73
		SX	2 ^A	1322	1111	800						
	POS	SX	86Z1 P	1969	1656	350	K784		601K5370000			
	POS	SX	86Z2 P	1726	1452	400	K784		601K5370000			
	POS	SX	86Z3 P	1458	1226	450	K784		601K5370000			
	POS	SX	86Z4 P	1010	849	500	K784		601K5370000			
16S160 A	13.85	POS	SX	2300 P 1 ^A	1806	1538	345	K246		601K5450000		
16S160 A	17.47		SX	2 ^A	1806	1538	345					
		POS	SX	2310 P 1 ^A	1252	1066	420	K246		601K5450000		
			SX	2 ^A	1252	1066	420					
		POS	SX	2325 P	1806	1538	345	K246		601K5450000		
		POS	SX	2365 P	1252	1066	420	K246		601K5450000		
		POS	DX	81Z1 P	963	820	1000	K219		601K5450000		
		POS	SX	82Z1 P	1269	1081	300	K131	K710	601K5450000		
		POS	SX	83Z1 P 1 ^A	1269	1081	300	K131	K710	601K5450000		
			SX	2 ^A	1994	1698	200					
		POS	SX	86Z1 P	1733	1476	350	K781		601K5450000		81
		POS	SX	86Z2 P	1520	1294	400	K781		601K5450000		81
		POS	SX	86Z3 P	1284	1093	450	K781		601K5450000		81
		POS	SX	86Z4 P	889	757	500	K781		601K5450000		81
16S160 A	14.29	POS	SX	2300 P 1 ^A	1706	1388	345	K246		601K5450000		
16S190 A	17.47		SX	2 ^A	1706	1388	345					
		POS	SX	2310 P 1 ^A	1183	962	420	K246		601K5450000		
			SX	2 ^A	1183	962	420					
		POS	SX	2325 P	1706	1388	345	K246		601K5450000		
		POS	SX	2365 P	1183	962	420	K246		601K5450000		
		POS	DX	81Z1 P	910	740	1000	K219		601K5450000		
		POS	SX	82Z1 P	1199	975	300	K131	K710	601K5450000		
		POS	SX	83Z1 P 1 ^A	1199	975	300	K131	K710	601K5450000		
			SX	2 ^A	1885	1533	200					
		POS	SX	86Z1 P	1638	1332	350	K781		601K5450000		81
		POS	SX	86Z2 P	1436	1168	400	K781		601K5450000		81
		POS	SX	86Z3 P	1213	986	450	K781		601K5450000		81
		POS	SX	86Z4 P	840	683	500	K781		601K5450000		81
16S181	13.74	POS	SX	1865 P	1196	1001	420	K290		601K5170000		
16S221 (NEW)	13.74	POS	SX	2300 P 1 ^A	1725	1444	345	K246		601K5360000		71
			SX	2 ^A	1725	1444	345					
		POS	SX	2310 P 1 ^A	1196	1001	420	K246		601K5360000		71
			SX	2 ^A	1196	1001	420					
		POS	SX	2325 P	1725	1444	345	K301		601K5490000		71



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

Z.F.

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sens de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapter mntg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes
				VELsu	VELno		STD	SE/R				
	POS	SX	2365 P	1196	1001	420	K246		601K5360000			71
16S190 A 11.74	POS	SX	2300 P 1 ^A	1819	1538	345	K246		601K5450000			
		SX	2 ^A	1819	1538	345						
	POS	SX	2310 P 1 ^A	1261	1066	420	K246		601K5450000			
		SX	2 ^A	1261	1066	420						
	POS	SX	2325 P	1819	1538	345	K246		601K5450000			
	POS	SX	2365 P	1261	1066	420	K246		601K5450000			
	POS	DX	81Z1 P	970	820	1000	K219		601K5450000			
	POS	SX	82Z1 P	1278	1081	300	K131	K710	601K5450000			
	POS	SX	83Z1 P 1 ^A	1278	1081	300	K131	K710	601K5450000			
		SX	2 ^A	2009	1698	200						
	POS	SX	86Z1 P	1746	1476	350	K781		601K5450000			81
	POS	SX	86Z2 P	1531	1294	400	K781		601K5450000			81
POS	SX	86Z3 P	1293	1093	450	K781		601K5450000			81	
POS	SX	86Z4 P	895	757	500	K781		601K5450000			81	
16S220 13.8 16S220 16.47	POS	SX	2300 P 1 ^A	1725	1444	345	K488		601K5460000			
		SX	2 ^A	1725	1444	345						
	POS	SX	2310 P 1 ^A	1196	1001	420	K488		601K5460000			
		SX	2 ^A	1196	1001	420						
	POS	SX	2325 P	1725	1444	345	K488		601K5460000			
	POS	SX	2365 P	1196	1001	420	K488		601K5460000			
	POS	DX	81Z1 P	920	770	1000	K219		601K5460000			
	POS	SX	82Z1 P	1213	1015	300	K131	K710	601K5460000			
	POS	SX	83Z1 P 1 ^A	1213	1015	300	K131	K710	601K5460000			
		SX	2 ^A	1905	1595	200						
	POS	SX	86Z1 P	1656	1386	350	K781		601K5360000			81
	POS	SX	86Z2 P	1452	1215	400	K781		601K5360000			81
POS	SX	86Z3 P	1226	1026	450	K781		601K5360000			81	
POS	SX	86Z4 P	849	711	500	K781		601K5360000			81	
16S220 A 14.14	POS	SX	2300 P 1 ^A	1725	1444	345	K488		601K5460000			
		SX	2 ^A	1725	1444	345						
	POS	SX	2310 P 1 ^A	1196	1001	420	K246		601K5450000			
		SX	2 ^A	1196	1001	420						
	POS	SX	2325 P	1725	1444	345	K246		601K5450000			
	POS	SX	2365 P	1196	1001	420	K246		601K5450000			
	POS	DX	81Z1 P	920	770	1000	K219		601K5450000			
	POS	SX	82Z1 P	1213	1015	300	K131	K710	601K5450000			
	POS	SX	83Z1 P 1 ^A	1213	1015	300	K131	K710	601K5450000			
		SX	2 ^A	1905	1595	200						
	POS	SX	86Z1 P	1656	1386	350	K781		601K5450000			81
	POS	SX	86Z2 P	1452	1215	400	K781		601K5450000			81
POS	SX	86Z3 P	1226	1026	450	K781		601K5450000			81	
POS	SX	86Z4 P	849	711	500	K781		601K5450000			81	
16S220 IT 13.8 16S220 IT 16.47	POS	SX	2300 P 1 ^A	1725	1444	345	K301		601K5490000			
		SX	2 ^A	1725	1444	345						
	POS	SX	2310 P 1 ^A	1196	1001	420	K301		601K5490000			
		SX	2 ^A	1196	1001	420						
	POS	SX	2325 P	1725	1444	345	K301		601K5490000			
	POS	DX	81Z1 P	920	770	1000	K302		601K5490000			

I dati riportati non sono vincolanti e possono subire variazioni senza preavviso - Technical specifications are not binding and can be changed without notice



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

Z.F.

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sens de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapter mntg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes
				VELsu	VELno		STD	SE/R				
	POS	SX	82Z1 P	1213	1015	300	K241	K240	601K5490000			
	POS	SX	83Z1 P 1 ^A	1213	1015	300	K241	K240	601K5490000			
		SX	2 ^A	1905	1595	200						
	POS	SX	86Z1 P	1656	1386	350	K784		601K5490000			
	POS	SX	86Z2 P	1452	1215	400	K784		601K5490000			
	POS	SX	86Z3 P	1226	1026	450	K784		601K5490000			
	POS	SX	86Z4 P	849	711	500	K784		601K5490000			
16S221 OD 0,84	13.86	POS	SX	1865 P	1422	1196	420	K290		601K5170000		
		POS	SX	2300 P 1 ^A	2051	1725	345	K246		601K5360000		71
			SX	2 ^A	2051	1725	345					
		POS	SX	2310 P 1 ^A	1422	1196	420	K246		601K5360000		71
			SX	2 ^A	1422	1196	420					
		POS	SX	2325 P	2051	1725	345	K246		601K5360000		71
		POS	SX	2365 P	1422	1196	420	K246		601K5360000		71
		POS	SX	2565 P 1 ^A	2051	1725	345	K290		601K5170000		
			SX	2 ^A	2051	1725	345					
		POS	SX	2566 P 1 ^A	1422	1196	420	K290		601K5170000		
			SX	2 ^A	1422	1196	420					
		POS	DX	81Z1 P	1094	920	1000	K219		601K5360000		
		POS	SX	82Z1 P	1442	1213	300	K131	K710	601K5360000		
		POS	SX	83Z1 P 1 ^A	1442	1213	300	K131	K710	601K5360000		
			SX	2 ^A	2266	1905	200					
		POS	SX	85ZA P 1 ^A	1322	1111	800	K500		601K5570000		73
			DX	2 ^A	1866	1570	500					
		POS	SX	85ZB P 1 ^A	1322	1111	800	K500		601K5570000		73
			SX	2 ^A	1322	1111	800					
		POS	SX	86Z1 P	1969	1656	350	K781		601K5360000		81
		POS	SX	86Z2 P	1726	1452	400	K781		601K5360000		81
		POS	SX	86Z3 P	1458	1226	450	K781		601K5360000		81
		POS	SX	86Z4 P	1010	849	500	K781		601K5360000		81
16S251 OD 0,84	13.38	POS	SX	2300 P 1 ^A	2051	1725	345	K246		601K5380000		72
16S251 OD 0.84	11.54		SX	2 ^A	2051	1725	345					
16S251 OD 0.84	13.8	POS	SX	2310 P 1 ^A	1422	1196	420	K246		601K5380000		72
16S251 OD 0.84	13.74		SX	2 ^A	1422	1196	420					
16S251 OD 0.84	13.86	POS	SX	2325 P	2051	1725	345	K246		601K5380000		72
		POS	SX	2365 P	1422	1196	420	K246		601K5380000		72
		POS	DX	81Z1 P	1094	920	1000	K219		601K5380000		
		POS	SX	82Z1 P	1442	1213	300	K131	K710	601K5380000		
		POS	SX	83Z1 P 1 ^A	1442	1213	300	K131	K710	601K5380000		
			SX	2 ^A	2266	1905	200					
		POS	SX	85ZA P 1 ^A	1322	1111	800	K500		601K5590000		73
			DX	2 ^A	1866	1570	500					
		POS	SX	85ZB P 1 ^A	1322	1111	800	K500		601K5590000		73
			SX	2 ^A	1322	1111	800					
		POS	SX	86Z1 P	1969	1656	350	K781		601K5380000		81
		POS	SX	86Z2 P	1726	1452	400	K781		601K5380000		81
		POS	SX	86Z3 P	1458	1226	450	K781		601K5380000		81
		POS	SX	86Z4 P	1010	849	500	K781		601K5380000		81
16S251 OD 0.84 IT	11.54	POS	SX	2300 P 1 ^A	2051	1725	345	K301		601K5390000		58
16S251 OD 0.84 IT	13.8		SX	2 ^A	2051	1725	345					



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

Z.F.

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sense de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapt. mntg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes /Notas
				VELsu	VELno		STD	SE/R				
16S251OD0.84 IT 13.38	POS	SX	2310 P 1^A	1422	1196	420	K301		601K5390000			58
16S251OD0.84 IT 13.74		SX	2 ^A	1422	1196	420						
16S251OD0.84 IT 13.86	POS	SX	2325 P	2051	1725	345	K301		601K5390000			58
	POS	SX	2365 P	1422	1196	420	K301		601K5390000			58
	POS	DX	81Z1 P	1094	920	1000	K302		601K5390000			
	POS	SX	82Z1 P	1442	1213	300	K241	K240	601K5390000			
	POS	SX	83Z1 P 1^A	1442	1213	300	K241	K240	601K5390000			
		SX	2 ^A	2266	1905	200						
	POS	SX	85ZA P 1^A	1322	1111	800	K735		601K5590000			73
		DX	2 ^A	1866	1570	500						
	POS	SX	85ZB P 1^A	1322	1111	800	K735		601K5590000			73
		SX	2 ^A	1322	1111	800						
	POS	SX	86Z1 P	1969	1656	350	K784		601K5390000			
	POS	SX	86Z2 P	1726	1452	400	K784		601K5390000			
	POS	SX	86Z3 P	1458	1226	450	K784		601K5390000			
	POS	SX	86Z4 P	1010	849	500	K784		601K5390000			
16S1620 TD 1.00 16.41	POS	SX	1865 P	1196	1001	420	K290		601K5170000			
16S1920 TD 1.00 16.41	POS	SX	2300 P 1^A	1725	1444	345	K246		601K5360000			71
16S2220 TD 1.00 16.41		SX	2 ^A	1725	1444	345						
	POS	SX	2310 P 1^A	1196	1001	420	K246		601K5360000			71
		SX	2 ^A	1196	1001	420						
	POS	SX	2325 P	1725	1444	345	K246		601K5360000			71
	POS	SX	2365 P	1196	1001	420	K246		601K5360000			71
	POS	SX	2565 P 1^A	1725	1444	345	K290		601K5170000			
		SX	2 ^A	1725	1444	345						
	POS	SX	2566 P 1^A	1196	1001	420	K290		601K5170000			
		SX	2 ^A	1196	1001	420						
	POS	DX	81Z1 P	920	770	1000	K219		601K5360000			
	POS	SX	82Z1 P	1213	1015	300	K131	K710	601K5360000			
	POS	SX	83Z1 P 1^A	1213	1015	300	K131	K710	601K5360000			
		SX	2 ^A	1905	1595	200						
	POS	SX	85ZA P 1^A	1111	930	800	K500		601K5570000			73
		DX	2 ^A	1570	1314	500						
	POS	SX	85ZB P 1^A	1111	930	800	K500		601K5570000			73
		SX	2 ^A	1111	930	800						
	POS	SX	86Z1 P	1656	1386	350	K781		601K5360000			81
	POS	SX	86Z2 P	1452	1215	400	K781		601K5360000			81
	POS	SX	86Z3 P	1226	1026	450	K781		601K5360000			81
	POS	SX	86Z4 P	849	711	500	K781		601K5360000			81
16S1621 TD 1.00 16.41	POS	SX	1865 P	1196	1001	420	K290		601K5170000			58
16S2221 TD 1.00 16.41	POS	SX	2300 P 1^A	1725	1444	345	K301		601K5370000			58
		SX	2 ^A	1725	1444	345						
	POS	SX	2310 P 1^A	1196	1001	420	K301		601K5370000			58
		SX	2 ^A	1196	1001	420						
	POS	SX	2325 P	1725	1444	345	K301		601K5370000			58
	POS	SX	2365 P	1196	1001	420	K301		601K5370000			58
	POS	SX	2565 P 1^A	1725	1444	345	K290		601K5170000			58
		SX	2 ^A	1725	1444	345						
	POS	SX	2566 P 1^A	1196	1001	420	K290		601K5170000			58
		SX	2 ^A	1196	1001	420						



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

Z.F.

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sens de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapter mntg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes
				VELsu	VELno		STD	SE/R				
	POS	DX	81Z1 P	920	770	1000	K302		601K5370000			
	POS	SX	82Z1 P	1213	1015	300	K241	K240	601K5370000			
	POS	SX	83Z1 P 1 ^A	1213	1015	300	K241	K240	601K5370000			
		SX	2 ^A	1905	1595	200						
	POS	SX	85ZA P 1 ^A	1111	930	800	K735		601K5570000		73	
		DX	2 ^A	1570	1314	500						
	POS	SX	85ZB P 1 ^A	1111	930	800	K735		601K5570000		73	
		SX	2 ^A	1111	930	800						
	POS	SX	86Z1 P	1656	1386	350	K784		601K5370000			
	POS	SX	86Z2 P	1452	1215	400	K784		601K5370000			
	POS	SX	86Z3 P	1226	1026	450	K784		601K5370000			
	POS	SX	86Z4 P	849	711	500	K784		601K5370000			
16S1820 TO 0,84	13.8	POS	SX	1865 P	1422	1196	420	K290		601K5170000		
		POS	SX	2102 P	1442	1213	250	K138		601K5140000		
		POS	SX	2230 P 1 ^A	1431	1203	250	K131	K185	601K5140000		
			SX	2 ^A	2188	1840	140					
		POS	DX	2233 P	1094	920	590	K102		601K5140000		
		POS	SX	2300 P 1 ^A	2051	1725	345	K246		601K5360000		71
			SX	2 ^A	2051	1725	345					
		POS	SX	2302 P	1431	1203	250	K131	K185	601K5140000		
		POS	DX	2303 P	1094	920	590	K219		601K5140000		
		POS	SX	2310 P 1 ^A	1422	1196	420	K246		601K5360000		71
			SX	2 ^A	1422	1196	420					
		POS	SX	2325 P	2051	1725	345	K246		601K5360000		71
		POS	SX	2365 P	1422	1196	420	K246		601K5360000		71
		POS	SX	2565 P 1 ^A	2051	1725	345	K290		601K5170000		
			SX	2 ^A	2051	1725	345					
		POS	SX	2566 P 1 ^A	1422	1196	420	K290		601K5170000		
			SX	2 ^A	1422	1196	420					
		POS	DX	81Z1 P	1094	920	1000	K219		601K5360000		
		POS	SX	82Z1 P	1442	1213	300	K131	K710	601K5360000		
		POS	SX	83Z1 P 1 ^A	1442	1213	300	K131	K710	601K5360000		
			SX	2 ^A	2266	1905	200					
		POS	SX	84Z1 P	1413	1189	430	K726	K732	601K5360000		
		POS	SX	84Z3 P	981	825	500	K726	K732	601K5360000		
		POS	SX	85ZA P 1 ^A	1322	1111	800	K500		601K5570000		73
			DX	2 ^A	1866	1570	500					
		POS	SX	85ZB P 1 ^A	1322	1111	800	K500		601K5570000		73
			SX	2 ^A	1322	1111	800					
		POS	SX	86Z1 P	1969	1656	350	K781		601K5360000		81
		POS	SX	86Z2 P	1726	1452	400	K781		601K5360000		81
		POS	SX	86Z3 P	1458	1226	450	K781		601K5360000		81
		POS	SX	86Z4 P	1010	849	500	K781		601K5360000		81
16S1821 TO 0,84	13.8	POS	SX	1865 P	1422	1196	420	K290		601K5170000		58
16S2521 TO 0.84	13.8	POS	SX	2300 P 1 ^A	2051	1725	345	K301		601K5370000		58
			SX	2 ^A	2051	1725	345					
		POS	SX	2310 P 1 ^A	1422	1196	420	K301		601K5370000		58
			SX	2 ^A	1422	1196	420					
		POS	SX	2325 P	2051	1725	345	K301		601K5370000		58
		POS	SX	2365 P	1422	1196	420	K301		601K5370000		58



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

Z.F.

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sense de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapter mntg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes
				VELsu	VELno		STD	SE/R				
	POS	SX	2565 P 1 ^A	2051	1725	345	K290		601K5170000			58
		SX	2 ^A	2051	1725	345						
	POS	SX	2566 P 1 ^A	1422	1196	420	K290		601K5170000			58
		SX	2 ^A	1422	1196	420						
	POS	DX	81Z1 P	1094	920	1000	K302		601K5370000			
	POS	SX	82Z1 P	1442	1213	300	K241	K240	601K5370000			
	POS	SX	83Z1 P 1 ^A	1442	1213	300	K241	K240	601K5370000			
		SX	2 ^A	2266	1905	200						
	POS	SX	85ZA P 1 ^A	1322	1111	800	K735		601K5570000			73
		DX	2 ^A	1866	1570	500						
	POS	SX	85ZB P 1 ^A	1322	1111	800	K735		601K5570000			73
		SX	2 ^A	1322	1111	800						
	POS	SX	86Z1 P	1969	1656	350	K784		601K5370000			
	POS	SX	86Z2 P	1726	1452	400	K784		601K5370000			
	POS	SX	86Z3 P	1458	1226	450	K784		601K5370000			
	POS	SX	86Z4 P	1010	849	500	K784		601K5370000			
16S1921 TD 1.00	16.41	POS	SX	1865 P	1196	1001	420	K290	601K5170000			58
		POS	SX	2300 P 1 ^A	1725	1444	345	K301	601K5370000			58
			SX	2 ^A	1725	1444	345					
		POS	SX	2310 P 1 ^A	1196	1001	420	K301	601K5370000			58
			SX	2 ^A	1196	1001	420					
		POS	SX	2325 P	1725	1444	345	K301	601K5370000			58
		POS	SX	2365 P	1196	1001	420	K301	601K5370000			58
		POS	SX	2566 P 1 ^A	1196	1001	420	K290	601K5170000			58
			SX	2 ^A	1196	1001	420					
		POS	DX	81Z1 P	920	770	1000	K302	601K5370000			
		POS	SX	82Z1 P	1213	1015	300	K241	K240	601K5370000		
		POS	SX	83Z1 P 1 ^A	1213	1015	300	K241	K240	601K5370000		
			SX	2 ^A	1905	1595	200					
		POS	SX	85ZA P 1 ^A	1111	930	800	K735	601K5570000			73
			DX	2 ^A	1570	1314	500					
		POS	SX	85ZB P 1 ^A	1111	930	800	K735	601K5570000			73
			SX	2 ^A	1111	930	800					
		POS	SX	86Z1 P	1656	1386	350	K784	601K5370000			
		POS	SX	86Z2 P	1452	1215	400	K784	601K5370000			
		POS	SX	86Z3 P	1226	1026	450	K784	601K5370000			
		POS	SX	86Z4 P	849	711	500	K784	601K5370000			
16S2220 TO 0.84	13.8	POS	SX	1865 P	1422	1196	420	K290	601K5170000			
		POS	SX	2300 P 1 ^A	2051	1725	345	K246	601K5360000			71
			SX	2 ^A	2051	1725	345					
		POS	SX	2310 P 1 ^A	1422	1196	420	K246	601K5360000			71
			SX	2 ^A	1422	1196	420					
		POS	SX	2325 P	2051	1725	345	K246	601K5360000			71
		POS	SX	2365 P	1422	1196	420	K246	601K5360000			71
		POS	SX	2565 P 1 ^A	2051	1725	345	K290	601K5170000			
			SX	2 ^A	2051	1725	345					
		POS	SX	2566 P 1 ^A	1422	1196	420	K290	601K5170000			
			SX	2 ^A	1422	1196	420					
		POS	DX	81Z1 P	1094	920	1000	K219	601K5360000			
		POS	SX	82Z1 P	1442	1213	300	K131	K710	601K5360000		



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

Z.F.

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sens de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapter mtg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes
				VELsu	VELno		STD	SE/R				
					POS		SX	83Z1 P 1 ^A				
		SX	2 ^A	2266	1905	200						
	POS	SX	85ZA P 1 ^A	1322	1111	800	K500		601K5570000			73
		DX	2 ^A	1866	1570	500						
	POS	SX	85ZB P 1 ^A	1322	1111	800	K500		601K5570000			73
		SX	2 ^A	1322	1111	800						
	POS	SX	86Z1 P	1969	1656	350	K781		601K5360000			81
	POS	SX	86Z2 P	1726	1452	400	K781		601K5360000			81
	POS	SX	86Z3 P	1458	1226	450	K781		601K5360000			81
	POS	SX	86Z4 P	1010	849	500	K781		601K5360000			81
16S2221 TO 0.84	13.8	POS	SX	1865 P	1422	1196	420	K290		601K5170000		58
		POS	SX	2300 P 1 ^A	2051	1725	345	K301		601K5370000		58
		SX	2 ^A	2051	1725	345						
		POS	SX	2310 P 1 ^A	1422	1196	420	K301		601K5370000		58
		SX	2 ^A	1422	1196	420						
		POS	SX	2325 P	2051	1725	345	K301		601K5370000		58
		POS	SX	2365 P	1422	1196	420	K301		601K5370000		58
		POS	SX	2565 P 1 ^A	2051	1725	345	K301		601K5370000		58
		SX	2 ^A	2051	1725	345						
		POS	SX	2566 P 1 ^A	1422	1196	420	K301		601K5370000		58
		SX	2 ^A	1422	1196	420						
		POS	DX	81Z1 P	1094	920	1000	K302		601K5370000		
		POS	SX	82Z1 P	1442	1213	300	K241	K240	601K5370000		
		POS	SX	83Z1 P 1 ^A	1442	1213	300	K241	K240	601K5370000		
		SX	2 ^A	2266	1905	200						
		POS	SX	85ZA P 1 ^A	1322	1111	800	K735		601K5570000		73
		DX	2 ^A	1866	1570	500						
		POS	SX	85ZB P 1 ^A	1322	1111	800	K735		601K5570000		73
		SX	2 ^A	1322	1111	800						
		POS	SX	86Z1 P	1969	1656	350	K784		601K5370000		
		POS	SX	86Z2 P	1726	1452	400	K784		601K5370000		
		POS	SX	86Z3 P	1458	1226	450	K784		601K5370000		
		POS	SX	86Z4 P	1010	849	500	K784		601K5370000		
16S2520 TO 0.84	13.8	POS	SX	1865 P	1422	1196	420	K290		601K5170000		
		POS	SX	2300 P 1 ^A	2051	1725	345	K246		601K5360000		71
		SX	2 ^A	2051	1725	345						
		POS	SX	2310 P 1 ^A	1422	1196	420	K246		601K5360000		71
		SX	2 ^A	1422	1196	420						
		POS	SX	2325 P	2051	1725	345	K246		601K5360000		71
		POS	SX	2365 P	1422	1196	420	K246		601K5360000		71
		POS	SX	2565 P 1 ^A	2051	1725	345	K290		601K5170000		
		SX	2 ^A	2051	1725	345						
		POS	SX	2566 P 1 ^A	1422	1196	420	K290		601K5170000		
		SX	2 ^A	1422	1196	420						
		POS	DX	81Z1 P	1094	920	1000	K219		601K5360000		
		POS	SX	82Z1 P	1442	1213	300	K131	K710	601K5360000		
		POS	SX	83Z1 P 1 ^A	1442	1213	300	K131	K710	601K5360000		
		SX	2 ^A	2266	1905	200						
		POS	SX	85ZA P 1 ^A	1322	1111	800	K500		601K5570000		73
		DX	2 ^A	1866	1570	500						



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

Z.F.

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sense de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapt. mntg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes
				VELsu	VELno		STD	SE/R				
	POS	SX	85ZB P 1 ^A	1322	1111	800	K500		601K5570000			73
		SX	2 ^A	1322	1111	800						
	POS	SX	86Z1 P	1969	1656	350	K781		601K5360000			81
	POS	SX	86Z2 P	1726	1452	400	K781		601K5360000			81
	POS	SX	86Z3 P	1458	1226	450	K781		601K5360000			81
	POS	SX	86Z4 P	1010	849	500	K781		601K5360000			81
16S2720 TO 0.84	13.8	POS	2300 P 1 ^A	2051	1725	345	K246		601K5380000			72
		SX	2 ^A	2051	1725	345						
		POS	2310 P 1 ^A	1422	1196	420	K246		601K5380000			72
		SX	2 ^A	1422	1196	420						
		POS	2325 P	2051	1725	345	K246		601K5380000			72
		POS	2365 P	1422	1196	420	K246		601K5380000			72
		POS	81Z1 P	1094	920	1000	K219		601K5380000			
		POS	82Z1 P	1442	1213	300	K131	K710	601K5380000			
		POS	83Z1 P 1 ^A	1442	1213	300	K131	K710	601K5380000			
		SX	2 ^A	2266	1905	200						
		POS	85ZA P 1 ^A	1322	1111	800	K500		601K5590000			73
		DX	2 ^A	1866	1570	500						
		POS	85ZB P 1 ^A	1322	1111	800	K500		601K5590000			73
		SX	2 ^A	1322	1111	800						
		POS	86Z1 P	1969	1656	350	K781		601K5380000			81
		POS	86Z2 P	1726	1452	400	K781		601K5380000			81
		POS	86Z3 P	1458	1226	450	K781		601K5380000			81
		POS	86Z4 P	1010	849	500	K781		601K5380000			81
16S2721 TO 0.84	13.8	POS	2300 P 1 ^A	2051	1725	345	K301		601K5390000			58
		SX	2 ^A	2051	1725	345						
		POS	2310 P 1 ^A	1422	1196	420	K301		601K5390000			58
		SX	2 ^A	1422	1196	420						
		POS	2325 P	2051	1725	345	K301		601K5390000			58
		POS	2365 P	1422	1196	420	K301		601K5390000			58
		POS	81Z1 P	1094	920	1000	K302		601K5390000			
		POS	82Z1 P	1442	1213	300	K241	K240	601K5390000			
		POS	83Z1 P 1 ^A	1442	1213	300	K241	K240	601K5390000			
		SX	2 ^A	2266	1905	200						
		POS	85ZA P 1 ^A	1322	1111	800	K735		601K5590000			73
		DX	2 ^A	1866	1570	500						
		POS	85ZB P 1 ^A	1322	1111	800	K735		601K5590000			73
		SX	2 ^A	1322	1111	800						
		POS	86Z1 P	1969	1656	350	K784		601K5390000			
		POS	86Z2 P	1726	1452	400	K784		601K5390000			
		POS	86Z3 P	1458	1226	450	K784		601K5390000			
		POS	86Z4 P	1010	849	500	K784		601K5390000			
12AS1630 TD 1,0	15.86	POS	DX	1801 P		820	K207		601K510S000			47
12AS1930 TD 1,0	15.86	POS	SX	1802 P		1066	K271		601K521S000			47
12AS2140 TD 1,0	15.86	POS	SX	1865 P		1066	K272		601K5220000			47
12AS2340 TD 1,0	15.86	POS	SX	2420 P 1 ^A		1293	K303					47
12AS2540 TD 1,0	15.86		SX	2 ^A		2101						
		POS	SX	2421 P 1 ^A		1214	K303					47
			SX	2 ^A		1929						
		POS	SX	2422 P 1 ^A		1011	K303					47



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

Z.F.

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sens de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapt. mntg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes /Notas
				VELsu	VELno		STD	SE/R				
		SX	2 ^A		1517	540						
	POS	SX	2567 P 1 ^A		1538	345	K355		601K5310000			49
		SX	2 ^A		1538	345						
	POS	SX	2568 P 1 ^A		1066	420	K355		601K5310000			49
		SX	2 ^A		1066	420						
	POS	SX	2569 P		1538	345	K355		601K5310000			49
	POS	DX	81Z1 P		820	1000	K703		601K5400000			69
	POS	SX	82Z1 P		1081	300	K354	K711	601K5400000			69
	POS	SX	83Z1 P 1 ^A		1081	300	K345	K711	601K5400000			69
		SX	2 ^A		1698	200						
	POS	SX	86Z1 P		1476	350	K793		601K5400000			69
	POS	SX	86Z2 P		1294	400	K793		601K5400000			69
	POS	SX	86Z3 P		1093	450	K793		601K5400000			69
	POS	SX	86Z4 P		757	500	K793		601K5400000			69
12AS1631 TD 1,0	15.86	POS	DX	1801 P	820	590	K270		601K521S000			47
12AS1931 TD 1,0	15.86	POS	SX	1802 P	1066	295	K271		601K521S000			47
12AS2141 TD 1,0	15.86	POS	SX	1865 P	1066	420	K272		601K5220000			47
12AS2341 TD 1,0	15.86	POS	SX	2420 P 1 ^A	1293	640	K303					47
			SX	2 ^A	2101	390						
		POS	SX	2421 P 1 ^A	1214	730	K303					47
			SX	2 ^A	1929	425						
		POS	SX	2422 P 1 ^A	1011	890	K303					47
			SX	2 ^A	1517	540						
		POS	SX	2567 P 1 ^A	1538	345	K355		601K5310000			49
			SX	2 ^A	1538	345						
		POS	SX	2568 P 1 ^A	1066	420	K355		601K5310000			49
			SX	2 ^A	1066	420						
		POS	SX	2569 P	1538	345	K355		601K5310000			49
		POS	DX	81Z1 P	820	1000	K703		601K5400000			69
		POS	SX	82Z1 P	1081	300	K354	K711	601K5400000			69
		POS	SX	83Z1 P 1 ^A	1081	300	K345	K711	601K5400000			69
			SX	2 ^A	1698	200						
		POS	SX	86Z1 P	1476	350	K793		601K5400000			69
		POS	SX	86Z2 P	1294	400	K793		601K5400000			69
		POS	SX	86Z3 P	1093	450	K793		601K5400000			69
		POS	SX	86Z4 P	757	500	K793		601K5400000			69
12AS1800	14.88	POS	DX	1801 P	760	590	K207		601K510S000			47
		POS	SX	1802 P	988	295	K271		601K521S000			47
		POS	SX	1865 P	988	420	K272		601K5220000			47
		POS	SX	2420 P 1 ^A	1199	640	K303					47
			SX	2 ^A	1948	390						
		POS	SX	2421 P 1 ^A	1126	730	K303					47
			SX	2 ^A	1788	425						
		POS	SX	2422 P 1 ^A	937	890	K303					47
			SX	2 ^A	1406	540						
		POS	SX	2567 P 1 ^A	1425	345	K355		601K5310000			49
			SX	2 ^A	1425	345						
		POS	SX	2568 P 1 ^A	988	420	K355		601K5310000			49
			SX	2 ^A	988	420						
		POS	SX	2569 P	1425	345	K355		601K5310000			49



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

Z.F.

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sens de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapter mntg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes
				VELsu	VELno		STD	SE/R				
	POS	DX	81Z1 P		760	1000	K703		601K5400000			69
	POS	SX	82Z1 P		1002	300	K354	K711	601K5400000			69
	POS	SX	83Z1 P 1 ^A		1002	300	K345	K711	601K5400000			69
		SX	2 ^A		1574	200						
	POS	SX	86Z1 P		1368	350	K793		601K5400000			69
	POS	SX	86Z2 P		1199	400	K793		601K5400000			69
	POS	SX	86Z3 P		1013	450	K793		601K5400000			69
	POS	SX	86Z4 P		701	500	K793		601K5400000			69
12AS1800-IT	14.88	POS	DX	1801 P	760	590	K270		601K521S000			47
		POS	SX	1802 P	988	295	K271		601K521S000			47
		POS	SX	1865 P	988	420	K272		601K5220000			47
		POS	SX	2420 P 1 ^A	1199	640	K303					47
			SX	2 ^A	1948	390						
		POS	SX	2421 P 1 ^A	1126	730	K303					47
			SX	2 ^A	1788	425						
		POS	SX	2422 P 1 ^A	937	890	K303					47
			SX	2 ^A	1406	540						
		POS	SX	2567 P 1 ^A	1425	345	K355		601K5310000			49
			SX	2 ^A	1425	345						
		POS	SX	2568 P 1 ^A	988	420	K355		601K5310000			49
			SX	2 ^A	988	420						
		POS	SX	2569 P	1425	345	K355		601K5310000			49
		POS	DX	81Z1 P	760	1000	K703		601K5400000			69
		POS	SX	82Z1 P	1002	300	K354	K711	601K5400000			69
		POS	SX	83Z1 P 1 ^A	1002	300	K345	K711	601K5400000			69
			SX	2 ^A	1574	200						
		POS	SX	86Z1 P	1368	350	K793		601K5400000			69
		POS	SX	86Z2 P	1199	400	K793		601K5400000			69
		POS	SX	86Z3 P	1013	450	K793		601K5400000			69
		POS	SX	86Z4 P	701	500	K793		601K5400000			69
12AS1930TO 0,78	12.33	POS	DX	1801 P	1350	590	K207		601K510S000			47
12AS2330TO 0,78	12.33	POS	SX	1802 P	1755	295	K271		601K521S000			47
		POS	SX	1865 P	1755	420	K272		601K5220000			47
		POS	SX	2420 P 1 ^A	2129	640	K303					47
			SX	2 ^A	3459	390						
		POS	SX	2421 P 1 ^A	1999	730	K303					47
			SX	2 ^A	3177	425						
		POS	SX	2422 P 1 ^A	1665	890	K303					47
			SX	2 ^A	2498	540						
		POS	SX	2567 P 1 ^A	2531	345	K355		601K5310000			49
			SX	2 ^A	2531	345						
		POS	SX	2568 P 1 ^A	1755	420	K355		601K5310000			49
			SX	2 ^A	1755	420						
		POS	SX	2569 P	2531	345	K355		601K5310000			49
		POS	DX	81Z1 P	1350	1000	K703		601K5400000			69
		POS	SX	82Z1 P	1779	300	K354	K711	601K5400000			69
		POS	SX	83Z1 P 1 ^A	1779	300	K345	K711	601K5400000			69
			SX	2 ^A	2796	200						
		POS	SX	86Z1 P	2430	350	K793		601K5400000			69
		POS	SX	86Z2 P	2130	400	K793		601K5400000			69



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

Z.F.

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sens de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapter mntg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes /Notas
				VELsu	VELno		STD	SE/R				
	POS	SX	86Z3 P		1800	450	K793		601K5400000			69
	POS	SX	86Z4 P		1246	500	K793		601K5400000			69
12AS1931TO 0,78 12.33	POS	DX	1801 P		1350	590	K270		601K521S000			47
12AS2131TO 0,78 12.33	POS	SX	1802 P		1755	295	K271		601K521S000			47
12AS2331TO 0,78 12.33	POS	SX	1865 P		1755	420	K272		601K5220000			47
	POS	SX	2420 P 1 ^A		2129	640	K303					47
		SX	2 ^A		3459	390						
	POS	SX	2421 P 1 ^A		1999	730	K303					47
		SX	2 ^A		3177	425						
	POS	SX	2422 P 1 ^A		1665	890	K303					47
		SX	2 ^A		2498	540						
	POS	SX	2567 P 1 ^A		2531	345	K355		601K5310000			49
		SX	2 ^A		2531	345						
	POS	SX	2568 P 1 ^A		1755	420	K355		601K5310000			49
		SX	2 ^A		1755	420						
	POS	SX	2569 P		2531	345	K355		601K5310000			49
	POS	DX	81Z1 P		1350	1000	K703		601K5400000			69
	POS	SX	82Z1 P		1779	300	K354	K711	601K5400000			69
	POS	SX	83Z1 P 1 ^A		1779	300	K345	K711	601K5400000			69
		SX	2 ^A		2796	200						
	POS	SX	86Z1 P		2430	350	K793		601K5400000			69
	POS	SX	86Z2 P		2130	400	K793		601K5400000			69
	POS	SX	86Z3 P		1800	450	K793		601K5400000			69
	POS	SX	86Z4 P		1246	500	K793		601K5400000			69
12AS2130TO 0,78 12.33	POS	DX	1801 P		1350	590	K207		601K510S000			47
	POS	SX	1802 P		1755	295	K271		601K521S000			47
	POS	SX	1865 P		1755	420	K272		601K5220000			47
	POS	SX	2420 P 1 ^A		2129	640	K303					
		SX	2 ^A		3459	390						
	POS	SX	2421 P 1 ^A		1999	730	K303					47
		SX	2 ^A		3177	425						
	POS	SX	2422 P 1 ^A		1665	890	K303					47
		SX	2 ^A		2498	540						
	POS	SX	2567 P 1 ^A		2531	345	K355		601K5310000			49
		SX	2 ^A		2531	345						
	POS	SX	2568 P 1 ^A		1755	420	K355		601K5310000			49
		SX	2 ^A		1755	420						
	POS	SX	2569 P		2531	345	K355		601K5310000			49
	POS	DX	81Z1 P		1350	1000	K703		601K5400000			69
	POS	SX	82Z1 P		1779	300	K354	K711	601K5400000			69
	POS	SX	83Z1 P 1 ^A		1779	300	K345	K711	601K5400000			69
		SX	2 ^A		2796	200						
	POS	SX	86Z1 P		2430	350	K793		601K5400000			69
	POS	SX	86Z2 P		2130	400	K793		601K5400000			69
	POS	SX	86Z3 P		1800	450	K793		601K5400000			69
	POS	SX	86Z4 P		1246	500	K793		601K5400000			69
12AS2301 0,78 12.33	POS	DX	1801 P		1350	590	K207		601K510S000			47
	POS	SX	1802 P		1755	295	K271		601K521S000			47
	POS	SX	1865 P		1755	420	K272		601K5220000			47
	POS	SX	2420 P 1 ^A		2129	640	K303					47



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

Z.F.

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sense de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapter mtg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes /Notas
				VELsu	VELno		STD	SE/R				
		SX	2 ^A		3459	390						
	POS	SX	2421 P 1 ^A		1999	730	K303					47
		SX	2 ^A		3177	425						
	POS	SX	2422 P 1 ^A		1665	890	K303					47
		SX	2 ^A		2498	540						
	POS	SX	2567 P 1 ^A		2531	345	K355		601K5310000			49
		SX	2 ^A		2531	345						
	POS	SX	2568 P 1 ^A		1755	420	K355		601K5310000			49
		SX	2 ^A		1755	420						
	POS	SX	2569 P		2531	345	K355		601K5310000			49
	POS	DX	81Z1 P		1350	1000	K703		601K5400000			69
	POS	SX	82Z1 P		1779	300	K354	K711	601K5400000			69
	POS	SX	83Z1 P 1 ^A		1779	300	K345	K711	601K5400000			69
		SX	2 ^A		2796	200						
	POS	SX	86Z1 P		2430	350	K793		601K5400000			69
	POS	SX	86Z2 P		2130	400	K793		601K5400000			69
	POS	SX	86Z3 P		1800	450	K793		601K5400000			69
	POS	SX	86Z4 P		1246	500	K793		601K5400000			69
12AS2301 0,78IT	12.33	POS	DX	1801 P	1350	590	K270		601K521S000			47
		POS	SX	1802 P	1755	295	K271		601K521S000			47
		POS	SX	1865 P	1755	420	K272		601K5220000			47
		POS	SX	2420 P 1 ^A	2129	640	K303					47
			SX	2 ^A	3459	390						
	POS	SX	2421 P 1 ^A		1999	730	K303					47
		SX	2 ^A		3177	425						
	POS	SX	2422 P 1 ^A		1665	890	K303					47
		SX	2 ^A		2498	540						
	POS	SX	2567 P 1 ^A		2531	345	K355		601K5310000			49
		SX	2 ^A		2531	345						
	POS	SX	2568 P 1 ^A		1755	420	K355		601K5310000			49
		SX	2 ^A		1755	420						
	POS	SX	2569 P		2531	345	K355		601K5310000			49
	POS	DX	81Z1 P		1350	1000	K703		601K5400000			69
	POS	SX	82Z1 P		1779	300	K354	K711	601K5400000			69
	POS	SX	83Z1 P 1 ^A		1779	300	K345	K711	601K5400000			69
		SX	2 ^A		2796	200						
	POS	SX	86Z1 P		2430	350	K793		601K5400000			69
	POS	SX	86Z2 P		2130	400	K793		601K5400000			69
	POS	SX	86Z3 P		1800	450	K793		601K5400000			69
	POS	SX	86Z4 P		1246	500	K793		601K5400000			69
12AS2301 1,0	15.86	POS	DX	1801 P	820	590	K207		601K510S000			47
		POS	SX	1802 P	1066	295	K271		601K521S000			47
		POS	SX	1865 P	1066	420	K272		601K5220000			47
		POS	SX	2420 P 1 ^A	1293	640	K303					47
			SX	2 ^A	2101	390						
	POS	SX	2421 P 1 ^A		1214	730	K303					47
		SX	2 ^A		1929	425						
	POS	SX	2422 P 1 ^A		1011	890	K303					47
		SX	2 ^A		1517	540						
	POS	SX	2567 P 1 ^A		1538	345	K355		601K5310000			49



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

Z.F.

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sense de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapt. mntg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes /Notas
				VELsu	VELno		STD	SE/R				
		SX	2 ^A		1538	345						
	POS	SX	2568 P 1 ^A		1066	420	K355		601K5310000			49
		SX	2 ^A		1066	420						
	POS	SX	2569 P		1538	345	K355		601K5310000			49
	POS	DX	81Z1 P		820	1000	K703		601K5400000			69
	POS	SX	82Z1 P		1081	300	K354	K711	601K5400000			69
	POS	SX	83Z1 P 1 ^A		1081	300	K345	K711	601K5400000			69
		SX	2 ^A		1698	200						
	POS	SX	86Z1 P		1476	350	K793		601K5400000			69
	POS	SX	86Z2 P		1294	400	K793		601K5400000			69
	POS	SX	86Z3 P		1093	450	K793		601K5400000			69
	POS	SX	86Z4 P		757	500	K793		601K5400000			69
12AS2301 1,0-IT	15.86	POS	DX	1801 P	820	590	K270		601K521S000			47
		POS	SX	1802 P	1066	295	K271		601K521S000			47
		POS	SX	1865 P	1066	420	K272		601K5220000			47
		POS	SX	2420 P 1 ^A	1293	640	K303					47
			SX	2 ^A	2101	390						
	POS	SX	2421 P 1 ^A		1214	730	K303					47
		SX	2 ^A		1929	425						
	POS	SX	2422 P 1 ^A		1011	890	K303					47
		SX	2 ^A		1517	540						
	POS	SX	2567 P 1 ^A		1538	345	K355		601K5310000			49
		SX	2 ^A		1538	345						
	POS	SX	2568 P 1 ^A		1066	420	K355		601K5310000			49
		SX	2 ^A		1066	420						
	POS	SX	2569 P		1538	345	K355		601K5310000			49
	POS	DX	81Z1 P		820	1000	K703		601K5400000			69
	POS	SX	82Z1 P		1081	300	K354	K711	601K5400000			69
	POS	SX	83Z1 P 1 ^A		1081	300	K345	K711	601K5400000			69
		SX	2 ^A		1698	200						
	POS	SX	86Z1 P		1476	350	K793		601K5400000			69
	POS	SX	86Z2 P		1294	400	K793		601K5400000			69
	POS	SX	86Z3 P		1093	450	K793		601K5400000			69
	POS	SX	86Z4 P		757	500	K793		601K5400000			69
12AS2541 TD 1,0	15.86	POS	DX	1801 P	820	590	K270		601K521S000			47
		POS	SX	1802 P	1066	295	K271		601K521S000			47
		POS	SX	1865 P	1066	420	K272		601K5220000			47
		POS	SX	2420 P 1 ^A	1293	640	K303					47
			SX	2 ^A	2101	390						
	POS	SX	2422 P 1 ^A		1011	890	K303					47
		SX	2 ^A		1517	540						
	POS	SX	2567 P 1 ^A		1538	345	K355		601K5310000			49
		SX	2 ^A		1538	345						
	POS	SX	2568 P 1 ^A		1066	420	K355		601K5310000			49
		SX	2 ^A		1066	420						
	POS	SX	2569 P		1538	345	K355		601K5310000			49
	POS	DX	81Z1 P		820	1000	K703		601K5400000			69
	POS	SX	82Z1 P		1081	300	K354	K711	601K5400000			69
	POS	SX	83Z1 P 1 ^A		1081	300	K345	K711	601K5400000			69
		SX	2 ^A		1698	200						



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

Z.F.

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sens de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapt. mntg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes /Notas
				VELsu	VELno		STD	SE/R				
	POS	SX	86Z1 P		1476	350	K793		601K5400000			69
	POS	SX	86Z2 P		1294	400	K793		601K5400000			69
	POS	SX	86Z3 P		1093	450	K793		601K5400000			69
	POS	SX	86Z4 P		757	500	K793		601K5400000			69
16AS2200	15.89	POS	DX	1801 P		712	590	K207		601K510S000		47
	POS	SX	1802 P		926	295	K271		601K521S000			47
	POS	SX	1865 P		926	420	K272		601K5220000			47
	POS	SX	2420 P 1 ^A		1123	640	K303					47
		SX	2 ^A		1824	390						
	POS	SX	2421 P 1 ^A		1054	730	K303					47
		SX	2 ^A		1675	425						
	POS	SX	2422 P 1 ^A		878	890	K303					47
		SX	2 ^A		1317	540						
	POS	SX	2567 P 1 ^A		1335	345	K355		601K5310000			49
		SX	2 ^A		1335	345						
	POS	SX	2568 P 1 ^A		926	420	K355		601K5310000			49
		SX	2 ^A		926	420						
	POS	SX	2569 P		1335	345	K355		601K5310000			49
	POS	DX	81Z1 P		712	1000	K703		601K5400000			69
	POS	SX	82Z1 P		938	300	K354	K711	601K5400000			69
	POS	SX	83Z1 P 1 ^A		938	300	K345	K711	601K5400000			69
		SX	2 ^A		1475	200						
	POS	SX	86Z1 P		1282	350	K793		601K5400000			69
	POS	SX	86Z2 P		1124	400	K793		601K5400000			69
	POS	SX	86Z3 P		949	450	K793		601K5400000			69
	POS	SX	86Z4 P		657	500	K793		601K5400000			69
16AS2200-IT	15.89	POS	DX	1801 P		712	590	K270		601K521S000		47
	POS	SX	1802 P		926	295	K271		601K521S000			47
	POS	SX	1865 P		926	420	K272		601K5220000			47
	POS	SX	2420 P 1 ^A		1123	640	K303					47
		SX	2 ^A		1824	390						
	POS	SX	2421 P 1 ^A		1054	730	K303					47
		SX	2 ^A		1675	425						
	POS	SX	2422 P 1 ^A		878	890	K303					47
		SX	2 ^A		1317	540						
	POS	SX	2567 P 1 ^A		1335	345	K355		601K5310000			49
		SX	2 ^A		1335	345						
	POS	SX	2568 P 1 ^A		926	420	K355		601K5310000			49
		SX	2 ^A		926	420						
	POS	SX	2569 P		1335	345	K355		601K5310000			49
	POS	DX	81Z1 P		712	1000	K703		601K5400000			69
	POS	SX	82Z1 P		938	300	K354	K711	601K5400000			69
	POS	SX	83Z1 P 1 ^A		938	300	K345	K711	601K5400000			69
		SX	2 ^A		1475	200						
	POS	SX	86Z1 P		1282	350	K793		601K5400000			69
	POS	SX	86Z2 P		1124	400	K793		601K5400000			69
	POS	SX	86Z3 P		949	450	K793		601K5400000			69
	POS	SX	86Z4 P		657	500	K793		601K5400000			69
16AS2230 TD 1,0	17.03	POS	DX	1801 P		760	590	K207		601K510S000		47
	POS	SX	1802 P		988	295	K271		601K521S000			47



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

Z.F.

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sens de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapter mtg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes
				VELsu	VELno		STD	SE/R				
	POS	SX	1865 P		988	420	K272		601K5220000			47
	POS	SX	2420 P 1 ^A		1199	640	K303					47
		SX	2 ^A		1948	390						
	POS	SX	2421 P 1 ^A		1126	730	K303					47
		SX	2 ^A		1788	425						
	POS	SX	2422 P 1 ^A		937	890	K303					47
		SX	2 ^A		1406	540						
	POS	SX	2567 P 1 ^A		1425	345	K355		601K5310000			49
		SX	2 ^A		1425	345						
	POS	SX	2568 P 1 ^A		988	420	K355		601K5310000			49
		SX	2 ^A		988	420						
	POS	SX	2569 P		1425	345	K355		601K5310000			49
	POS	DX	81Z1 P		760	1000	K703		601K5400000			69
	POS	SX	82Z1 P		1002	300	K354	K711	601K5400000			69
	POS	SX	83Z1 P 1 ^A		1002	300	K345	K711	601K5400000			69
		SX	2 ^A		1574	200						
	POS	SX	86Z1 P		1368	350	K793		601K5400000			69
	POS	SX	86Z2 P		1199	400	K793		601K5400000			69
	POS	SX	86Z3 P		1013	450	K793		601K5400000			69
	POS	SX	86Z4 P		701	500	K793		601K5400000			69
16AS2231 TD 1,0	17.03	POS	DX	1801 P		760	590	K270		601K521S000		47
		POS	SX	1802 P		988	295	K271		601K521S000		47
		POS	SX	1865 P		988	420	K272		601K5220000		47
		POS	SX	2420 P 1 ^A		1199	640	K303				47
			SX	2 ^A		1948	390					
		POS	SX	2421 P 1 ^A		1126	730	K303				47
			SX	2 ^A		1788	425					
		POS	SX	2422 P 1 ^A		937	890	K303				47
			SX	2 ^A		1406	540					
		POS	SX	2567 P 1 ^A		1425	345	K355		601K5310000		49
			SX	2 ^A		1425	345					
		POS	SX	2568 P 1 ^A		988	420	K355		601K5310000		49
			SX	2 ^A		988	420					
		POS	SX	2569 P		1425	345	K355		601K5310000		49
		POS	DX	81Z1 P		760	1000	K703		601K5400000		69
		POS	SX	82Z1 P		1002	300	K354	K711	601K5400000		69
		POS	SX	83Z1 P 1 ^A		1002	300	K345	K711	601K5400000		69
			SX	2 ^A		1574	200					
		POS	SX	86Z1 P		1368	350	K793		601K5400000		69
		POS	SX	86Z2 P		1199	400	K793		601K5400000		69
		POS	SX	86Z3 P		1013	450	K793		601K5400000		69
		POS	SX	86Z4 P		701	500	K793		601K5400000		69
16AS2601 0,83	14.12	POS	DX	1801 P		1110	590	K207		601K510S000		47
		POS	SX	1802 P		1443	295	K271		601K521S000		47
		POS	SX	1865 P		1443	420	K272		601K5220000		47
		POS	SX	2420 P 1 ^A		1750	640	K303				47
			SX	2 ^A		2844	390					
		POS	SX	2421 P 1 ^A		1644	730	K303				47
			SX	2 ^A		2612	425					
		POS	SX	2422 P 1 ^A		1369	890	K303				47



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

Z.F.

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sens de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapter mntg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes /Notas
				VELsu	VELno		STD	SE/R				
		SX	2 ^A		2054	540						
	POS	SX	2567 P 1 ^A		2081	345	K355		601K5310000			49
		SX	2 ^A		2081	345						
	POS	SX	2568 P 1 ^A		1443	420	K355		601K5310000			49
		SX	2 ^A		1443	420						
	POS	SX	2569 P		2081	345	K355		601K5310000			49
	POS	DX	81Z1 P		1110	1000	K703		601K5400000			69
	POS	SX	82Z1 P		1463	300	K354	K711	601K5400000			69
	POS	SX	83Z1 P 1 ^A		1463	300	K345	K711	601K5400000			69
		SX	2 ^A		2299	200						
	POS	SX	86Z1 P		1998	350	K793		601K5400000			69
	POS	SX	86Z2 P		1752	400	K793		601K5400000			69
	POS	SX	86Z3 P		1480	450	K793		601K5400000			69
	POS	SX	86Z4 P		1025	500	K793		601K5400000			69
16AS2601 0,83IT	14.12	POS	DX	1801 P	1110	590	K270		601K521S000			47
		POS	SX	1802 P	1443	295	K271		601K521S000			47
		POS	SX	1865 P	1443	420	K272		601K5220000			47
		POS	SX	2420 P 1 ^A	1750	640	K303					47
			SX	2 ^A	2844	390						
	POS	SX	2421 P 1 ^A		1644	730	K303					47
		SX	2 ^A		2612	425						
	POS	SX	2422 P 1 ^A		1369	890	K303					47
		SX	2 ^A		2054	540						
	POS	SX	2567 P 1 ^A		2081	345	K355		601K5310000			49
		SX	2 ^A		2081	345						
	POS	SX	2568 P 1 ^A		1443	420	K355		601K5310000			49
		SX	2 ^A		1443	420						
	POS	SX	2569 P		2081	345	K355		601K5310000			47
	POS	DX	81Z1 P		1110	1000	K703		601K5400000			69
	POS	SX	82Z1 P		1463	300	K354	K711	601K5400000			69
	POS	SX	83Z1 P 1 ^A		1463	300	K345	K711	601K5400000			69
		SX	2 ^A		2299	200						
	POS	SX	86Z1 P		1998	350	K793		601K5400000			69
	POS	SX	86Z2 P		1752	400	K793		601K5400000			69
	POS	SX	86Z3 P		1480	450	K793		601K5400000			69
	POS	SX	86Z4 P		1025	500	K793		601K5400000			69
16AS2601 1,0	17.03	POS	DX	1801 P	760	590	K207		601K510S000			47
		POS	SX	1802 P	988	295	K271		601K521S000			47
		POS	SX	1865 P	988	420	K272		601K5220000			47
		POS	SX	2420 P 1 ^A	1199	640	K303					47
			SX	2 ^A	1948	390						
	POS	SX	2421 P 1 ^A		1126	730	K303					47
		SX	2 ^A		1788	425						
	POS	SX	2422 P 1 ^A		937	890	K303					47
		SX	2 ^A		1406	540						
	POS	SX	2567 P 1 ^A		1425	345	K355		601K5310000			49
		SX	2 ^A		1425	345						
	POS	SX	2568 P 1 ^A		988	420	K355		601K5310000			49
		SX	2 ^A		988	420						
	POS	SX	2569 P		1425	345	K355		601K5310000			49



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

Z.F.

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sens de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapter mtg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes /Notas
				VELsu	VELno		STD	SE/R				
	POS	DX	81Z1 P		760	1000	K703		601K5400000			69
	POS	SX	82Z1 P		1002	300	K354	K711	601K5400000			69
	POS	SX	83Z1 P 1 ^A		1002	300	K345	K711	601K5400000			69
		SX	2 ^A		1574	200						
	POS	SX	86Z1 P		1368	350	K793		601K5400000			69
	POS	SX	86Z2 P		1199	400	K793		601K5400000			69
	POS	SX	86Z3 P		1013	450	K793		601K5400000			69
	POS	SX	86Z4 P		701	500	K793		601K5400000			69
16AS2601 1,0-IT	17.03	POS	DX	1801 P	760	590	K270		601K521S000			47
		POS	SX	1802 P	988	295	K271		601K521S000			47
		POS	SX	1865 P	988	420	K272		601K5220000			47
		POS	SX	2420 P 1 ^A	1199	640	K303					47
			SX	2 ^A	1948	390						
		POS	SX	2421 P 1 ^A	1126	730	K303					47
			SX	2 ^A	1788	425						
		POS	SX	2422 P 1 ^A	937	890	K303					47
			SX	2 ^A	1406	540						
		POS	SX	2567 P 1 ^A	1425	345	K355		601K5310000			49
			SX	2 ^A	1425	345						
		POS	SX	2568 P 1 ^A	988	420	K355		601K5310000			49
			SX	2 ^A	988	420						
		POS	SX	2569 P	1425	345	K355		601K5310000			49
		POS	DX	81Z1 P	760	1000	K703		601K5400000			69
		POS	SX	82Z1 P	1002	300	K354	K711	601K5400000			69
		POS	SX	83Z1 P 1 ^A	1002	300	K345	K711	601K5400000			69
			SX	2 ^A	1574	200						
		POS	SX	86Z1 P	1368	350	K793		601K5400000			69
		POS	SX	86Z2 P	1199	400	K793		601K5400000			69
		POS	SX	86Z3 P	1013	450	K793		601K5400000			69
		POS	SX	86Z4 P	701	500	K793		601K5400000			69
16AS2630TO 0,83	14.12	POS	DX	1801 P	1110	590	K207		601K510S000			47
		POS	SX	1802 P	1443	295	K271		601K521S000			47
		POS	SX	1865 P	1443	420	K272		601K5220000			47
		POS	SX	2420 P 1 ^A	1750	640	K303					47
			SX	2 ^A	2844	390						
		POS	SX	2421 P 1 ^A	1644	730	K303					47
			SX	2 ^A	2612	425						
		POS	SX	2422 P 1 ^A	1369	890	K303					47
			SX	2 ^A	2054	540						
		POS	SX	2567 P 1 ^A	2081	345	K355		601K5310000			49
			SX	2 ^A	2081	345						
		POS	SX	2568 P 1 ^A	1443	420	K355		601K5310000			49
			SX	2 ^A	1443	420						
		POS	SX	2569 P	2081	345	K355		601K5310000			49
		POS	DX	81Z1 P	1110	1000	K703		601K5400000			69
		POS	SX	82Z1 P	1463	300	K354	K711	601K5400000			69
		POS	SX	83Z1 P 1 ^A	1463	300	K345	K711	601K5400000			69
			SX	2 ^A	2299	200						
		POS	SX	86Z1 P	1998	350	K793		601K5400000			69
		POS	SX	86Z2 P	1752	400	K793		601K5400000			69



TABELLA PRESE DI FORZA
POWER TAKE OFFS
NEBENANTRIEBETABELLE
TABLEAU PRISE DE FORCE

Z.F.

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sense de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapt. mtg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes
				VELsu	VELno		STD	SE/R				
	POS	SX	86Z3 P		1480	450	K793		601K5400000			69
	POS	SX	86Z4 P		1025	500	K793		601K5400000			69
16AS2631TO 0,83	14.12	POS	DX	1801 P		1110	590	K270		601K521S000		47
		POS	SX	1802 P		1443	295	K271		601K521S000		47
		POS	SX	1865 P		1443	420	K272		601K5220000		47
		POS	SX	2420 P 1 ^A		1750	640	K303				47
			SX	2 ^A		2844	390					
		POS	SX	2421 P 1 ^A		1644	730	K303				47
			SX	2 ^A		2612	425					
		POS	SX	2422 P 1 ^A		1369	890	K303				47
			SX	2 ^A		2054	540					
		POS	SX	2567 P 1 ^A		2081	345	K355		601K5310000		49
			SX	2 ^A		2081	345					
		POS	SX	2568 P 1 ^A		1443	420	K355		601K5310000		49
			SX	2 ^A		1443	420					
		POS	SX	2569 P		2081	345	K355		601K5310000		49
		POS	DX	81Z1 P		1110	1000	K703		601K5400000		69
		POS	SX	82Z1 P		1463	300	K354	K711	601K5400000		69
		POS	SX	83Z1 P 1 ^A		1463	300	K345	K711	601K5400000		69
			SX	2 ^A		2299	200					
		POS	SX	86Z1 P		1998	350	K793		601K5400000		69
		POS	SX	86Z2 P		1752	400	K793		601K5400000		69
		POS	SX	86Z3 P		1480	450	K793		601K5400000		69
		POS	SX	86Z4 P		1025	500	K793		601K5400000		69
5 S 270 (DX)	4.994	DX	DX	22Z1 M		1000	120	K787				
5 S 270 (SX)	4.994	SX	DX	20Z1 M		1000	120	K006				
		SX	DX	21Z1 M		1983	20	K006				
5 S 640	5.72	DX/SX	DX	2241 P		775	250	K491				
6 S 350 VD	6.7	DX	DX	22Z2 M		953	180	K787				
S5-200	4.994	A	SX	DX	20Z1 M	1000	120	K006				
			SX	DX	21Z1 M	1983	20	K006				
S6-300		A	SX	DX	20Z2 M	910	180	K006				
			SX	DX	21Z2 M	2026	20	K006				
S6-350		A	DX	DX	22Z2 E	953	180	K787				
5-30	7.31	DX	DX	2077 P		859	200	K082				
5-30	8	DX	DX	2077 P		783	200	K082				
5-30	8.5	DX	DX	2077 P		734	200	K082				
6-36 / 0,80	6.93	DX	DX	2186 P		1047	250	K153			6036SP17800	
		POS	SX	2311 P 1 ^A		956	345	K246				
			SX	2 ^A		956	345					
		POS	SX	2312 P 1 ^A		663	420	K246				
			SX	2 ^A		663	420					
		POS	SX	2345 P		956	345	K246				
		POS	SX	2351 P		663	420	K246				
		POS	DX	81Z2 P		510	600	K219				
		POS	SX	82Z2 P		672	300	K719	K720			
		POS	SX	82Z3 P		672	300	K719	K720			43
		POS	SX	83Z2 P 1 ^A		672	300	K719	K720			
			SX	2 ^A		1056	200					



TABELLA PRESE DI FORZA
 POWER TAKE OFFS
 NEBENANTRIEBETABELLE
 TABLEAU PRISE DE FORCE

Z.F.

05/03/2003

CAMBIO DI VELOCITA' GEARBOX GETRIEBE BOITE DE VITESSE	Lato montaggio Mounting side Montageseite Côté de montage	Senso rotazione Rotation sense Drehrichtung Sens de rotation	PDF PTO Na. PDF	VELOCITA' SPEED DREHZAHL VITESSE		Coppia uscita Output torque Drehmoment Couple	Kit montaggio Mounting kit Montagesatz Kit de montage		ADATTATORE ADAPTER ADAPTER ADAPTEUR	SPESSORE SPACER DISTANZSTCK EPAISSEUR	Kit mont. adatt. Adapt. mntg. kit Adp. montagesatz Kit de mont. adapt.	Note /Notes /Notes
				VEL _{su}	VEL _{no}		STD	SE/R				
					POS		SX	83Z3 P 1 [^]				
		SX	2 [^]		1056	200						
	POS	SX	86Z5 P		918	350	K781					
	POS	SX	86Z6 P		805	400	K781					
	POS	SX	86Z7 P		680	450	K781					
	POS	SX	86Z8 P		471	500	K781					